


\$2.50


Nov/Dec 1981



for 6800 and 6809 users









SMOKE SIGNAL BROADCASTING



31336 VIA COLINAS

WESTLAKE VILLAGE, CA 91362

TEL (213) 889-9340 / TWX 910-494-4965

SMOKE SIGNAL DEALERS ARE INTO THE 1980s WITH A PROGRAM FOR RECORD PROFITS

- Ask any Smoke Signal Dealer what support really means!
- At Smoke Signal, we believe that support means more than merely shipping computers to you. Our theory is that the technical aspects and marketing strategies are also important keys to a FULL support program. The difference between us and the "other guys" is that we believe in **serving people**. With us, it isn't a numbers game to achieve growth at any cost, as it seems to be with all too many other manufacturers.
- Smoke Signal's multi-faceted marketing campaign is customized to you and your business plans. Marketing support goes much further than just running ads in magazines. Our **Dealer Information Exchange** is a major marketing tool for the Smoke Signal **Dealer**. It's an intelligence network that keeps you closely in touch with worldwide CHIEFTAIN™ computer applications. This unique program opens lines of communication, and

the result is a clear BENEFIT for everyone in the loop . . particularly Smoke Signal Dealers and their customers!

• PRODUCTS: Our 6800/6809-based computer systems meet all of your customers' needs. Our systems range from single-user DOS69D or FLEX; 5½-inch and 8-inch systems all the way up to the 10-Megabyte and 30-Megabyte 8-inch Winchester-based computer systems running OS-9 Multi-User, Multi-Tasking Operating Systems.

All of our products are ENDURANCE CERTIFIED®; an exclusive Smoke Signal quality control measure that positively verifies a component is free of defects, and meets or exceeds all specifications. We employ in-house engineers, technicians and programmers who are available to you if you ever need assistance.


We offer one of the most flexible Dealer Programs and Discount Schedules available in the computer industry today . . .

MAYBE YOU SHOULD CONSIDER JOINING THE TRIBE.

Contact Deborah Conrad (213) 889-9340 for further information.

SMOKE ARE WI FOR	SIGN INTO TH A F RECOL	AL DEAL THE 19 PROGRA RD PRO	LERS 80s AM OFITS.	
\			CONSI TRIBE.	DER

☐ Send me Smoke Signal's Dealer Pro☐ Send me the packet and also call m☐ Send the name of my local Smoke S	ne at the following number: ()
Name	Title
Company	
Address	
City	State



Versatile, Two-Channel Serial I/O Card \$59.95

- Optional on-card bit rate generator (BRG) especially convenient for extended addressing bus where system clock is not available.
- Optional bit rate generator provides seven standard rates, from 110 bits/second to 19200 bits/ second.
- Transmit rate and receive rate of each channel may be individually selected.
- On-card ACIAs (asynchronous communications interface adapters) may be clocked with the MPU system clock.
- Design minimizes software overhead yet allows full control of data.
- Compatible with both older and newer versions of the System-30 bus.

System Requirements: An SIO card occupies four continuous memory bytes: Bytes 0 and 1 are control, status and data for channel A; bytes 2 and 3 are control, status and data for channel B.



PERCOM DATA COMPANY, INC. 11220 PAGEMILL RD. DALLAS, TX 75243 (214) 340-7081 Toll-free Order Number 1-800-527-1592

- Compatible with either 16- or 4-byte boundary addressing.
- Communications signals are compatible with RS-232-C levels. Clock signals are TTL.
- Low prices: A Serial I/O card is only \$59.95, only \$74.95 with optional bit rate generator installed.
 The bit rate generator may also be purchased as an add-on kit for only \$19.95.

PRICES AND SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE.
© 1981 PERCOM DATA COMPANY, Inc.

	Yes I'd like to know more about the Percom two-channel serial communications interface module. Rush me free literature.
	Send to PERCOM DATA COMPANY, Inc., Dept. 50-S01 11220 Pagemill Rd. Dallas, TX 75243
	name
	streef
	city state
	zip phone number
I	Mail today!



tm

Publisher/Editor Ken Orme

Assistant Publisher/Editor Robert Wood

> Review Editor Gary Manning

Office Manager Typesetting/Camera Bonnie J. Orme

Copyright © 1981
by SS-50 Computing
ALL RIGHTS RESERVED
Material in this publication
may not be reproduced
in any manner
without prior permission
in writing.

SS-50 Computing 133 North Mayfield Ave. Garland, Utah 84312

Send Correspondence To:

SS-50 Computing P.O. Box 398 Garland, Utah 84312 Phone [801] 257-5733

Subscription Rates:

1 Year [6 Issues] - \$12.00 2 Years [12 Issues] - \$22.00

Canada/Mexico - \$14.00 per Year All other countries - \$25.00 per Year [Airmail only] [U.S. Funds drawn on U.S. Banks]

ON THE COVER.. Three GIMIX disk contoller boards. On top you see the GIMIX DMA Controller for 5 and 8 inch drives. On the bottom left is the Double Density Disk Contoller, with the 5/8 Disk Controller Board on the right. For information, see the Gimix Ad on the back cover.

Contents

Nov/Dec 1981 Vol. 2 - No. 5

Editorial	4
Features and Reviews	
Magic Spell	
Book Review	
Software	.16
Life Open Door Detector	
Letters	5
New Products	. 20
	. 40

PLEASE forgive this issue for being late [again]...Just when we were getting caught-up, Myrphy's Law caught up to us. The typesetter broke down, and it took over 40 days to get the part from the manufacturer. We have now lengthened all expiration dates by two issues, except for the new subscribers. That should make-up for the problems caused to you.

Manuscripts submitted for publication should include sufficent return postage if needed to be returned. All materials should be original with full ownership rights by the said author. Programs submitted remain property of the author, with the exception that SS-50 Computing reserves the right to reprint the material in future publications.

We review products from every source and carry ALL of THE BEST

FOR COLOR PRODUCTS

We offer products from Mark Data • Micro Works Radio Shack • Book Publishers Epson • NEC • Centronics • Moore

SOFTWARE: Color Invaders • Color Pac Attack Monitor • Adventure Games • Text Editors Assemblers • PASCAL • Magikube Finance Programs • Color Data Organizer Graphic Games • Disassembler

HARDWARE: 32K RAM Expansion Board • 16K RAM Set Cables • Interfaces • Power Pack ROM Cartridge • Printers

ACCESSORIES: Books • Cassettes • Supplies • Service Manuals

Look to COMPUTERWARE for DISK SOFTWARE

* * * NEW PRODUCTS * * *

16 PLUS BOARD — just plug in to expand from 16K to 32K PAC ATTACK — graphics action game — PAC ATTACK 32K versions of Editor, Assembler, Monitor, PASCAL, BERSERK game — Micro Text (communications) — STAR BLASTER

Shipping from stock

CALL
OR
WRITE
FOR
COMPLETE
INFORMATION



Dept. C • Box 668
6809 Specialists Encinitas, CA 92024 • (714) 436-3512

Computerware is a trademark of Computerware.



by Ken Orme

If you are not aware, we have passed another point in SS-50 Bus history. For the second time we have seen the last of the SWTPC Computer kits. First it was the 6800 (no longer built or supported by Southwest Technical Products). Now it is the 6809 kit that is no longer sold. This is not to infer however, that they don't produce the 6809 in an assembled version.

I'm sure the reasons for the decision were all considered in depth before coming to the final conclusion, and there may be many reasons other than those I mention here. However, the main reason (as I was told by Dan Meyer at SWTPC) is due to the fact that Southwest did not want to go through all the problems of an FCC type approval for their "hobby" computers. A kit is considered a hobby computer. don't blame them for not wanting to go through that.

However, one facet of no longer producing a particular product is that sometimes has a detrimental effect on selling future products. People lose faith if something they buy suddenly nc longer is available or no longer is supported by the manufacturer.

Another facet deals with the fact that Southwest Technical no. longer is trying to sell to the "Hobbyist" market. That, by itself, may not be a problem to business, but how many sales will be lost to small business and industry by no longer trying to reach the hobby market? It seems many people tend to purchase computers for their business based on what they are familiar with on a hobby level. There are many SWTPC 6800's in school and industrial uses because of that one fact.

Still another facet of this is dropping one image and obtaining another. Since SWTPC has been in the hobby field for so long, it may take some time before the "business only" side of Southwest Technical catches on with the general public.

Conversely, some of the other SS-50 bus systems started out as business or industrial systems and

have not only a good number of years in this area behind them, but have a good reputation as a business system going already.

Many people feel that we owe a great deal to Southwest Technical for coming out with the 6800 and getting most of us started. I can see that point clearly. However, I still feel that SWTPC owes a lot to the hobbyist, too! Without those that bought the kits (the hobbyist) SWTPC would not be able to produce the systems that they are selling now. In fact, without the hobbyist, I feel the SWTPC Computer would not have survived. It took the combined efforts of engineers and consumers to get the systems "debugged" and to run properly. Just ask someone who bought the early systems if you don't believe me.

I feel that there is room for both markets for computers based on the SS-50 bus. It's true that the SS-50 hobby market is not the biggest in the industry, but it is still a good market. The hobbyist has been loyal for many years. I hope that favor can be repaid.

[SS-50]



LETTERS

Dear Editor,

I need sources for software and help. Your newsletter is very helpful.

> A. Lucas Laguna Hills, CA

Dear Editor,

I would like to see more information on SSB and less on FLEX.

Ronald Baxter Hayward, CA

We will be bringing more software for all machines and operating systems. It seems like the biggest problem comes from getting people to submit articles. After all, it is quite a chore to do the articles for everything. I suppose the reason FLEX is seen more often is that there are more people who have FLEX at this time.

Editor

Dear Editor:

Enclosed is my subscription for SS-50. I recently reviewed your magazine while purchasing a monitor "Humbug" from Star Kits. Your magazine looks great. Also I think your readers should know how superb Pete Stark of Star-Kits handled my inquiry.

Being only 15 miles away, he invited me over to try out his "Humbug". Well after trying it out, there was little doubt that it is head and shoulders over the one I was using. This monitor

"Humbug" will perform so many tasks and quickly (too). It will do hex dumps, ASCII dumps, find 1 - 2 - or 3 bytes, boot my DOS, move memory, compare memory and others. The best ones are a built-in disassembler and single stepping with each step listing all registers. Great for machine code programming.

To top all this it is menu fed for us oldies with poor memories. I think anyone doing serious programming should use Humbug.

> R. Scappatura New York

We received a letter some time ago from Richard G. Cagle with regard to his patch to move SWTPC disk BASIC from Mini-FLEX to FLEX 2.0. He offers to do you a service by providing a copy of the article he wrote, the source code, and a binary code all for just sending him a formatted disk with appropriate return postage, or a cash equivalent. The disk to send should be a 5¼ FLEX 2.0 formatted disk.

Anyone wishing to take advantage of this generous offer should contact Richard at: 11103 Sagepark Lane, Houston, TX 77089.

Editor

Dear Editor:

I have for sale: SWTP CT-64 Terminal with 9 inch video monitor. RS-232 interface, up to 1200 baud, all options installed. Works fine. \$150.

Congratulations on the new format...looks good!

Paul Pennington 2912 Palmetto Drive Martinez, GA 30907 [404] 860-2934 Dear Editor,

Thank you for your response in the "OS9 Exchange" Sept/Oct issue to my recent letter. I am interested in learning as much as I can about OS9, as it appears to be a very good operating system.

However, you seem to have misinterpreted my third question, the one about adapting OS9 for non-standard peripherals. While your reply to this question was informative, I was really asking if Microware supplies instructions for writing I/O drivers and incorporating them into the system. (I am a fairly competent assembly language programmer.) If my present plans for my eventual 6809 system continue to be valid, my terminal and printer will be at non-standard port addresses and will have a nonstandard protocol for "talking" to the computer. Even my disk drive(s), when I get one or more, are likely to be at non-standard port addresses.

One sometimes useful capability of an operating system to automatically read commands from a file after being "booted". (The name of this file would have to be built into the initialization sequence.) When all commands in the file have been executed, or if the user aborts this process, or if the file is not present, the terminal would then be used for command input. This capability could be used for issuing an appropriate TMODE command for the terminal, or for automatically starting an application program, or for some other purpose. (There may be other ways of accomplishing this function.

As for the problem you mentioned of getting your printer to work with its "Inverted" busy/ready bit, I was reading an OS9 manual last April and I remember something about a device table which contains infor-

(Continued on page 20)

ANOTHER

"OPEN DOOR" DETECTOR

Leo Taylor 18 Ridge Court West West Haven, CT 06516

I'd like to contribute to the on-going series in SS-50 Computing called 'Open Door Patch'. This series is based on patches to FLEX disk drivers by William Hart and others to use the software to allow the disk to spin up to speed when accessed and to detect if a disk is in place.

I was enthusiastic about the patch when I read it in the Nov-Dec issue and after adding it to my FLEX source I was pleased to see it works as claimed. My enthusiasm waned when I noticed my file read speed had dropped. A few tests revealed the speed reduction to be 2:1 for minifloppies and 3:1 for 8 inch disks. I soon found out why.

FORMATTING

FLEX formats a disk with the sectors interleaved. This interleaving is done by NEWDISK and is transparent to the user. I've dug rather deep into FLEX formatting since I have written my own Universal Disk Formatter program that allows me to alter the interleaving. The 'open Door Patch' destroys all the speed

improvement that the interleaving accomplished. The patch requires that the disk revolve past the index hole after every sector so FLEX can no longer load two or three sectors per revolution. This is a fairly high price to pay for a DRIVE NOT READY error.

What is needed is a method to determine if a drive is ready that requires zero time. Software is not the answer since all drives must indicate ready status at once if you are going to access more than one drive in a program. The only way I can imagine doing this is with ahardwarecircuit per drive. Though not as easy as a software approach, hardware would be a 'no compromise' solution.

I set out to find the ideal design: two ICs maximum, fast acting, delay on startup, no foil cuts to drive, etc. I found the circuit didn't exist. The drive ready indicator used in eight inch drives was not acceptable since it didn't expect the drive to have motor control. My Shugart 800s will continue to indicate READY when the motor is unplugged! The only option was to design my own card.

THE CIRCUIT

The enclosed circuit will do the trick. It uses only two ICs, both of which can be ordered from most mail order dealers (Shugart uses these Ics in their drives). The board taps signals from the drive, but does not cut into any foils, thus not affecting the resale value of the drive. One board must be made for each drive, so I designed a small PC board so all my 6800 friends could take advantage of the circuit.

The ready signal is generated by a re-triggerable one-shot. The time delay is set to slightly over the period of the index pulses.

The drive will indicate ready only when index pulses are present and repeating at full speed. The delay for motor speed-up is supplied by a second timer which is set for about ½ second. This delay only occurs when the motor starts up. The circuit output is wire ORed with the remaining drives and connected to the controller. The F&D controller I use has the needed inverter to connect the ready signal to the 1771 IC.

Other controllers may have to have an inverter provided and a pullup resistor.

SOFTWARE

Unfortunately the work is not completed with the hardware construction. The TSC FLEX-2 disk drivers cannot handle the 1771 ready bit. In fact, FLEX goes crazy when the ready bit is used. I found it invaluable to include a switch on my controller to ground the common ready line so I could boot standard FLEX disks. I wrote a new driver using ideas form TSC and F&D that handles the ready bit properly as well as a few other improvements. I have switching for drive type (I use 5 and 8 inch) as done by F&D. I increased the seek speed to 20/10 msec which is acceptable for four drives; this can be adjusted to suit the user. I removed the headload delay from the read routine and added it to the seek routine. Seek will only

delay when the head NEEDS loading whereas read delayed 10 msec before every sector. With these drivers you can read SWTP fast disk format (used by 2 MHZ systems) at about 1.3 MHZ. Recent versions of NEWDISK had an unannounced sector interleaving change which makes the disk load very slowly (just like 'Open Door Patch'.


I will supply a copy of the driver to anyone who will send me a disk (5½ or 8 inch single-sided, single-density) as well as an assortment of other utilities I've written, such as my disk formatter.

As a guide for testing disk speed, a normal TSC FLEX-2 disk driver should read a 100 sector text file in 14 seconds using the command: List FILENAME 9999. Be sure to use a freshly initialized disk. If you measure 30 seconds, you are only reading 1 sector per revolution. A SWTP fast format disk can be read in 12 seconds.

				* WRITE SECTOR *	SECTOR		
BF07	80			WRITE1	BSR	SEEK	
BF09		AC			LDA A	##PAC	
BFOB			34		TST	FBFLAG	
BFOE		01			BEG	WRITE2	
BF10	3				SWI		
BF11	01			WRITEZ	MOP		
BF12	PP				SEI		
BF13	87	80	00		STA A	COMREG	WRITE COMMAND
BF16		EB				DELAY	
BF18	20	03			BRA	WRITES	GET FIRST BYTE
BF1A		80	13		STA A	DATREG	WRITE CHAR
BF1D	A6	00		WRITES	LDA A	×,0	GET CHAR FROM FCB

MINIFLOPPY READY DETECT

PIN NUMBERS FOR SA-400



*	DISK	DRIVER	FOR ACC	* DISK DRIVER FOR ACCUMULATOR I/O	170
*	CONTR	COLLERS	SUCH AS	CONTROLLERS SUCH AS SWTP MF68 OR	3 OR
*	F&D M	F&D MDI-1. T	THIS DRI	THIS DRIVER HAS THE	ħ
*	ADDIT	IONAL L	.061C FO	ADDITIONAL LOGIC FOR SELECTING THE	S THE
*	TYPE	OF DRIV	/E (5/8)	TYPE OF DRIVE (5/8), OPERATION	HIIM NO
*	8 INC	H DRIVE	S AT 1.	INCH DRIVES AT 1. 25 MHZ, AND	ND OPER-
*	ATION	WITH F	AST FOR	ATION WITH FAST FORMAT DISKS AT 1. 3	AT 1.3
*	MHZ.	HEAD ST	MHZ. HEAD STEPPING RATE	RATE IS S	IS SET UP FOR
*	20 MS	EC ON S	S INCH C	20 MSEC ON 5 INCH (10 MSEC ON 8 INCH)	A B INCH)
*	WHICH	IS ACC	EPTABLE	WHICH IS ACCEPTABLE FOR SA-400/SA-800	00/SA-800.
*					
*	ADDRE	* ADDRESS EQUATES	ITES		
*					
Ö	DRVREG EQU	EOI	\$8014	CONTR	CONTROLLER REGISTERS

Ca

USED BY F&D	FOREGROUND/BACKROUND	LOCATED HERE FLEX-2. FOR TO \$DEOO.	CURRENT DRIVE NUMBER	EAD POSITION (TRACK) NOT BEING ACCESSED. 1 2 3 4 4 5 5 7 7	OF ADDRESSES VECTORS +++ CLOCK +++	ER 2 = 0
\$8015 \$8018 \$8019 \$801A	\$AC34 \$AD00	MITH TABLE	READ1 WRITE1 VRIFY1 RESTR1 DRIVE1 OCHEK1 0 0	TRACK TABLE STORES HEAD FOR EACH DRIVE WHEN NOT KTBL FCB 0	BLOCK COPER 11AC 11D1 3004 3010 NO12 10D0 NO48	TYPE TABLE FOR F&D CONTROLLER FCB 0 FCB 0 FCB \$90
	EQU	OPERATION MOVE THE	CAMP CAMP CAMP CAMP CAMP CAMP CAMP CAMP	1ABLE ACH DR FCB	AUTO-CONFIGURE FOR 6809 USE PF TVECT FUB \$6 TVECT FUB	TYPE FCB FCB FCB
TYPREG COMREG TRKREG SECREG DATREG	FBFLAG	* LUMP * FOR 0 * 6809	READ WRITE VERIFY RESTOR DRIVE CHECK GCHECK DRIVEN	* TRACK * FOR E	* * AUTO-(* FOR 66 * INVECT OUTVEC ACIA TIMER TIMER SMI SMI PCV	* DRIVE * USED F DRVTYP
8015 8018 8019 801A 801B	AC34 AD00	BESO	BE80 7E BE B7 BE83 7E BF 07 BE86 7E BF 33 BE89 7E BF 43 BE87 7E BF 59 BE97 00 BE95 00 BE97 00	BE99 00 BE99 00 BE9E 00 BE9C 00 BE9C 00 BE9F 00 BEA1 00	BEA3 E1 AC BEA5 E1 D1 BEA7 80 04 BEA8 80 10 BEAB A0 00 BEAD A0 12 BEAF E0 D0 BEB1 A0 48	BEB3 00 BEB4 00 BEB5 90

		WITH DUMMY READ				RESTORE SPEED	FLAG WRITE PROTECT	FLAG NO DRIVE		MAX DRIVE NUMBER	>3 BECOMES ZERO SELECT DRIVE TRACK TBL OF OLD DRIV SAVE OLD TRACK REGIST SAVE ORIVE NUMBER	DRIVE TYPE
COMREG #2 WRITE3 #1 WRITE4	WAIT	SECTOR WI	##8C	FBFLAG VRIFY2 DOCGM #*18 CLRINT	TRACK ZERO	DRIVE1 #\$A DOCCOM #\$80 RESTR3	##40 RESTR2 ##B	L	FROM FCB	TEMPX 3, X #3, UNDERB	DRVREG COUNTUP TRKREG O, X DRIVEN	\$1A, X
INX LDA B BIT B BNE BIT B	BSR BIT B CLI	VERIFY LAST	LDA A	TST BEG SWI NOP SEI BSR BIT B	10		BIT B BEG LDA B CLC RTS	LDA B SEC RTS	T DRIVE	STX LDA A CMP A BLS	CLR A STA A BSR A LLDA B STA B STA A BSR	LDA A
WRITE4	CLRINT	* VERIF	VRIFYI	VRIFYZ	* RESTORE *	RESTR1	RESTR2	RESTR3	* SELECT	* DRIVE1	UNDERG	
BF1F 08 BF20 F6 80 18 BF23 C5 02 BF25 26 F3 BF27 C5 01 BF29 26 F5	BF2B 09 BF2C 8D C4 BF2E C5 5C BF30 01 BF31 0E		BF33 86 8C	BF35 7D AC 34 BF38 27 01 BF36 01 BF3C OF BF3D 8D AE BF3F C5 18 BF3F C5 18		28 88 88 88 88 88 88 88 88 88 88 88 88 8	BF4D C5 40 BF4F 27 02 BF51 C6 0B BF53 0C BF54 39	BF55 C6 OF BF57 OD BF58 39		BF59 FF BE 97 BF5C A6 03 BF5E B 03 BF60 23 01	4F BB7 BB7 FB BB7	BF72 A6 1A

B7 80 A6 00 B7 80	BF 00	55 50 56 50 56 80 58 14 09 14	BF91 FE BE 97 NO BF94 C6 80 BF96 0D BF97 39	* * *	BF98 A6 03 8(BF9A 81 04 BF9C 24 F3 BF9C 80 B9	3 S S S S S S S S S S S S S S S S S S S	BFA7 CE BE 98 CC BFAA F6 BE 95 BFAD 08 CC		NO ERROR(S) DETECT	FLEX DISK DRIVER	SYMBOL TABLE	ACIA BEA7 CHECK COUNT BFAD COUNTU DELAY3 BFO4 DELAY4 DRIVEN BE95 DRVREG IRG BEAB ISRDY	
m		NO HEAD LOAD		GET CHAR STORE IN FCB	WAIT FOR DATA	SET CONDITION CODES		DESIRED TRACK DESIRED SECTOR	HEAD LOAD AND SEEK SPEED) TO TAKE
06*		SEEK #\$88 FBFLAG READ2	COMREG DELAY READ4	DATREG o, X	COMREG #2 READ3 #1 READ4	WAIT #\$1C CLRINT	SECTOR B	DATREG DELAY SECREG	DELAY #\$1A COMREG DELAY	READY	FBFLAG WAIT2	COMREG #1 WAIT	FOR COMMAND TO TAKE DELAY2 DELAY4
FCB	* READ SECTOR	BSR LDA A TST BEG SWI NOP	SEI STA A BSR BRA	STA A	LDA B BIT B BNE BNE BNE	BSR BIT B	SEEK TRACK A	STA A BSR STA B	BSR STA A BSR A		BEG	LDA B BIT B BNE RTS	TIME BSR BSR RTS
	* READ	READ1		READ3	READ4			SEEK	DOCOM	* WAIT UNTIL	TIAM	WAITZ	* WASTE * DELAY DELAY2 DELAY3 DELAY4
		ω 4	8	13	00			18 18 19	8		4	00	
		9 28 9 AC 0 1	38	800	30328	151			1 4 8 B		PC 01	80 01 F3	888
9			2887		828888	200		87 F7				32 28	9899
BEB6		BEB7 BEB9 BEBE BEBE BEC0 BEC0	BEC2 BEC3 BEC6 BEC8	BECD	BEDS BEDS BEDS BEDS BEDS	BEDB BEDD BEDF		BEE1 BEE4 BEE6	BEED BEED BEFO		BEF2 BEF5 BEF7	BEFS BEFS BEFT BEFF	BF00 BF02 BF04 BF06

GET TRACK TRACK OF NEW DRIVE +++ DELAY FOR MOTOR +++ PRESENT TRACK TOUMNY SECTOR GET STATUS	BY DRIVE SCAN DRIVE >3 DRIVE > 4 SELECT HARDWARE		1 TSC ASSEMBLER PAGE	COLDS ADOO COMREG BO18 DELAY BFOO DELAY2 BFOO DELAY2 BFOO DELAY2 BFOO DELAY2 BFOO DELAY2 BFOO DOTROE BEAS INVECT BEAS NOTRO BESO RESTRI BFOO SEEK BEEI SWI BEAD TRKTBL BE99 TYPREG BO15 WRITE1 BFOO WRITE2 BF11
STA A TYPREG LDA A O,X STA A TKKREG JSR #\$1000 LDA A TKKREG CLR B SEK LDA B COMREG BPL ISRDY DEX MAITRDY LDX TEMPX LDA B #\$80	VE READY CAN SKIPPED SET TO SKIP A 3, X A #4 NOTRDY NOTRDY DAIVE!	LDX *TRKTBL-1 LDA B DRIVEN INX DEC B COUNT RTS COLDS	8-30-81	CLRINT BF30 CC DATREG 801B DB DDCOM BEED DF DDVTYP BEB3 FE MONITR BEAF NG GCHEKI BF98 RE READ4 BED0 RE SECREG 8019 TF VRIFG 8019 TF VRIFE BEB3 WE
80 15 00 19 BF 00 10 00 80 19 WAITRD BE E1 80 18 14 F1 F1 F1 80 80	* CHECK DRIVE * ANY DRIVE * CURRENTLY * CURRENTLY * CURP * CHEK1 LDA * CMP F3 BES * BES * BES * CHEK1 LDA * CMP * CM	BE 98 COUNTUP BE 95 COUNT FC	S) DETECTED	TABLE: 7 CHECK BESF 4 DELAY4 BF04 5 DRVRG 8014 B ISRDY BF02 1 QCHECK BE92 1 QCHECK BE92 1 READ3 BECA 3 RESTR3 BF55 7 TIMER BF95 9 VERIFY BE84 8 WAITE4 BF20
BF74 B7 BF77 A6 BF77 B7 BF77 B7 BF77 B7 BF77 CE BF82 B6 BF83 SF BF85 SF BF86 C2A BF86 C2A BF86 C2A BF86 C3A BF87 C3A BF97 C3A	BF98 A6 BF94 81 BF97 24 BF96 80 BFA2 75 BFA3 00	BFA7 CE BFAA F6 BFAD 08 BFAE 5A BFAE 2A BFB1 39	NO ERROR(S) DI FLEX DISK DRIVER	SYMBOL TA ACIA BEA7 COUNT BFAD DELAY3 BF04 DRIVEN BE95 IRG BE81 PCV BE81 READ2 BEC1 READ2 BEC1 READ2 BEC3 READ2 BEC3 UNDER3 BF63 WAITE3 BF1A
	•			

MAGIC SPELL REVIEW

by Ken Orme

One of the things that I have needed for a long time is a spelling checker. I'm sure that most of you have noticed a few spelling errors in almost everything written or published. Some are "typographical" errors put there when things were typeset and others probably came about through neglect. Still, we don't claim to be the most perfect publication out of all the computer magazines like one magazine has. But, the means now exists where we can all produce more correct copy. This comes from Magic Spell (tm) from Star-Kits. Magic Spell is a program designed to check text files for spelling and typographical errors. It is an extremely useful program for anyone doing writing and/or word processing.

When we received our copy of Magic Spell several months ago, I had no idea how the program would handle so many formats of text files. After all, there are several different types of text editors and processors each one

with a slightly different set of codes on the disk. Well, after using the program for some time now, I dare say it will do a nice job with any text file in FLEX.

Briefly, Magic Spell compares each word in your text file against a dictionary file and prints out every word which does not appear in the dictionary. As you might realize, even a dictionary file with over 10,000 words (as this one has) will not be able to contain every word that you may use. Therefore, you have several other options rather than just have the program run.

The first option is to ignore the questionable word. If Magic Spell comes upon a word that is not in the dictionary, it will ask what you would like to do with the displayed word. If you type "I" it will then ignore that word and not print it or mark it. This is especially important if you have many words that are technical in nature or abbreviations that are used and you know that they are correct as written. After you type an I, Magic Spell goes on to the

next word.

Another option that is available is "M", to mark the word that is displayed. If you are certain the word is misspelled, or if you are not sure, this will probably be the thing to use. If you want it marked, it will also mark the source file with three asterisks after the incorrect word. This makes it easy to find with almost any editor available. If you would like Magic Spell to change the word for you in the text, there is an option for that, too. When this part of the option is selected, you will type in the correct word, rather than having the program get something out of context. And as I explain later, some of the text is printed on the screen so that you may see the word in context.

The third option is to type an "A" which means to add the word to the dictionary so that it will be there in the future. This is one of the best parts of the Magic Spell program. It allows you build your dictionary to the point where you have almost all the "unique"

words for your future use. This feature also allows you to add names and other words or abbreviations that are often used.

The fourth option is the fast mark option. It will allow you to mark all the words automatically without other prompts. This makes it a fast method to send questionable words to the printer, or if you want to "walk away" while it works, you can do so. Needless to say, this option uses the "F" to select it.

A fifth option is "Q", to quit and return to the DOS.

The thing that I like most about Magic Spell, is the fact that it does not make the corrections in the text for you, unless you choose to have it do so. It lets you know of probable errors and can mark them for you, but gives you the choice of making the actual corrections in the text of doing it for you. Why do I like this part of the package? Mainly because I use several different editors, and with a few of them it would make some difference in line length to have extra letters placed on a line, which in turn may not justify properly. Also, there are times when the context must be changed when an error is spotted, not just the word itself changed. Magic Spell does print out the previous three or four lines of text up to and including the word that is questionable so that you can see it in context and help you decide what to do.

As far as using Magic Spell is concerned, it is very straight forward and easy to operate. We have found it to be one of the easier programs to learn. It reminds me of some of the more lengthy utility programs such as FORMAT or NEWDISK. There are a few things to remember, but almost everything is given in the prompts.

The manual is very good as far as information on how to run the

program. It also includes examples that you can try on your machine. The manual includes information on how to output the words to the printer (for those not familiar with that), and information on reassembling the source code (which comes with it).

That is another nice feature about *Magic Spell*: the source code comes with the program. This allows you the opportunity to run the program on the 6800 or the 6809 and make different versions for different disk operating systems. One thing to remember, however, is that the source is not position independent. So those who wish to run it on OS-9 or UniFLEX will either have to rewrite the source or wait until it comes out on OS-9.

All the error messages are printed out so that you don't have to look up each one in the manual. Most errors that are serious will be fatal to the program, and will return to DOS. The more simple ones are those where you may forget to give the input file name, or where the file is not on the disk, etc.

Here are a few other things that you should know to see if this program will fit your needs. The words in the text file are allowed up to 31 characters. Anything longer is truncated. Hyphens at the end of the line are ignored, and the word is compared as though it were not hyphenated.

Peter Stark also makes the manual very comprehensive by including pages dealing with the source text file with more specific information on selecting "all" words or "selected" words to compare to the dictionary, and file name specifications. There is a lot of information on the dictionary file itself: how it is prepared, edited, etc. This section is extremely informative for those with limited disk size or those who may want to cut the

dictionary down for other reasons. Also, information on how to expand the dictionary size are included. One method given is to remove the end of file marker from the dictionary, and use a second or third disk to continue the dictionary. Then by adding the end of file marker to the end of the last disk, you will be able to have more than one disk for the dictionary. The one thing that is cautioned, however, is that the words must be in correct order whenever they are placed in the dictionary file.

The program is very powerful especially for the price. It is very seldom that you can find a program where the 10,000 plus word dictionary and the program are purchased for the price of this one, not alone a second program for another processor and the source code. And it all is less then \$90.00. There were only a couple of mistakes in the first dictionary files that went out, and since have been corrected. That is the only problem that I know of, since it has been running for us without a problem.

Since we received the Magic Spell program, Peter Stark has also come out with an expanded version of it for more serious applications. This version contains a 75,000 word dictionary and is designed for 6809 systems only. This version sells for less then \$240.00. The regular version of Magic Spell that we review here runs on both the 6800 and 6809 machines using FLEX, 6000 Mini-FLEX, and PERCOM systems. The OS-9 and SSB versions are being finished and will be available soon.

I feel that Magic Spell is a superior product and is just what you need if you do word processing, writing, or use you computer for other business applications where spelling is a factor.

[SS-50]

A 6809 "LIFE" Program

By Douglas Beck

The "Life" program is an interesting exercise in programming as well as being very interesting to watch perform on This version was the CRT. created some years ago by persons unknown, and fixed up to run under FLEX 9.0 when I got the 6809 CPU. In its present form it is not position independent. After considerable work, I finally arrived at the conclusion that independence was not worth the effort. A machine so occupied was not likely to be doing anything else.

The main features of this implementation are first, it is fast. Generations have to be delayed between displays to permit time to look at the pattern. Second, it does not depend on anyone's clone

of Mikbug to operate. If you have FLEX 9, that is enough, and is where the interface to the outside world should occur anyway. So many otherwise useful programs are cluttered by references to someone's very special ROM. These gadgets could be and should be replaced by operating system references or by constructing a library file that may be referenced by a LIB call in the Assembler.

Adaptation to your own system will require modification of the code at line 121 and again at line 127 to substitute the appropriate characters to control the "Clear screen" and "cursor home" function on your terminal or video display board.

included at the top of the display. There are no other special hardware requirements other than a minimum FLEX system and dumb terminal. I hope you enjoy

Running the program, once it is debugged involves invoking it as a command file. The program will prompt for entry of any character from the keyboard, after which it will clear the scree and begin creating display generations. Each key will cause a different initial generation to be created via the subroutine RAND. For starters, the "space" key will create a pattern that will run well over 400 generations. For the user's edification, a generation counter and population counter have been

the program as much as I have.

	print right margin	Print lower border	Start with Zero populn	this sentn	check if cell occupied	Ye S	check count of meighbor to determine whether to retain cell												
	TSTCEL #'I + OUTCH+ ROWLEN	OOP RLF← NE, PCR	*PLDATA* WAIT #0 POPULN	70	DR	+	#3 #4		YES	COUNT	POPULN 1, X	POPULN BASE OFFS	BASE XO XO XO	COUNT	BASE	BASE	XØ ROWLEN	E 000	
	BPL LDA LDA	DEC BPL JSR LEAX	JSR LBSR NEXT GENRN LDX STX	4-	LBSR LBSR	STA BSR Check neish	CMPA	CMPA	BNE	STA	LEAX	STX LDA	LDA	BSR	STA	STA	STA	2. P. S.	
	<u> </u>	ৰ দ ৷	*	COMP * See		÷			č	SET		NONE							
	F0 49 9F 0008 16	2F D8 9F 8004 8D 80F3	шы	3 GE	2F 808C 84	4 54 6 E	0 12 E	6 6 2	34	2D 2D	829 113	7 5 6 6 6 6 6 7 6 7 6	25 F	128	194	25 E	2E 16	25.2	
2	2133 2A 2135 86 2137 AD 2138 96 2130 97			2157 9F 2159 0F			2168 96 2168 81 2160 27		2172 ØD 2174 26			217F 9F 2181.96 2183 9B	2185 97 2187 96 2189 DE				2199 4C 2198 97 219C 91	2186 25 2180 0F 2182 D6	
	PAGE 1														1	doo Laur	gool		
	6-81 TSC ASSEMBLER a loose adaptation k Los Altos. CA	RAN 1	\$CD24 \$CD3C \$CD18 \$CD15 \$CD1E	\$CE84 \$CD83		64-1 15-1 \$10	TABLE 10000, 1000, 100, 10,·1 *	· N	000	V == ==	। स्व स्व ः	e4 e4 e-	1 1 4 9 9 5 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	\$605 *		A STATE CINES COLO INDESTA	-1,X inner timins loop W1 A	MØ	
	BI TSC A a loose	LBRA RAN Version	708 708 708 808 808	FA FDB \$CE84 S FDB \$CD@3 Stants wamamat	FCC .**		BASE FDB HEXBCD FDB HEXEND FOU	* Variables RND RMB	GENERN RMB 2	RAB		71 RMB 1 DX RMB 1 DY RMB 1	S RMB GIT RMB	TABLE1 RMB ENDTAB EQU	WAIT EQU * TIMEOL	PSHS A ##FFF	-1, X inner W1 A	* NO WO	
	7-16-81 TSC A "Life" game, a toose by Doug Beck Los Alt	2044 LIFE LBRA RAN Version * Vectors	CRLF FDB PR18 FDB OUTCH FDB INCH FDB PDGTA FDB	PLDATA FDB \$CE84 MARMS FDB \$CD03 * Constants MAGK ETP YOURSEL	700 700 ** 1	ROWLEN FCB COLLEN FCB OFFS FCB	50 FDB	* Variables RND RMB	N RMB	RAB			R W W W W W W	RMB	2036 WAIT EGU * TIME +:	02 WO PSHS A #\$FFF	LEAX -1, X inner BNE W1 PULS A	F2 BNE RTS	

Ę		68 64 4 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6	k for no. neishbor	effective addr
.v o new senrn	. #	BNE LOOP BAST Tisht neighb then reset move down one row LDA #-1 STA DX LDA DY INCA BY STA DY CMPA #2 BNE LOOP TST DY BNE LOOP	Check	U 10 10
B YOUNG SWITCH TO OFFS	* #-1 DX COUNT NEIGHB DX TST1 #2 P DX	isht Luup down one row #-1 DX DY A #2 LOOP LOOP	A X X X X X X X X X X X X X X X X X X X	X1 X1 X1 X1 X1 X1 X1
INCB STB CMPB CMPB BLS BLS ADDA STA NEG LBRA	CELL EQU LDX STX CORP STX CORP BSR CORP CORP	70	** NEIGHB ERU LDA ADDA LDB ADDB TST TST TST TST NI RTS	CADDR EGU STA ANDB STB LDA C1 ASL
* ;	2186 CELL 32 32 2D 1E 100P 14 02 32 100P 14	* * * * * T	21 DD NE:	Z1EE CAI
27- 177- 189- 189- 189- 179-	32 32 32 32 32 32 32	4 428 8384 4		30 117 30 30
2164 SC 2165 D7 2167 D1 2169 23 2169 98 2167 97 2167 97 2187 16	2186 8E 2189 9F 2189 9F 2181 0C 2101,27 2103 8E 2103 9B	21C9 86 21C9 86 21C6 96 21C6 47 21D2 81 21D2 81 21D4 28 21D7 80 21D7 80		21EE 97 21F0 D4 21F2 D7 21F4 96 21F6 48 21F8 48
E	b 			
Gen random Oth gene Ask for seed set it from kbd begin randomize		until TO IT		generation zero population at least 1
for seed it from kbd in randomize	do 00 00 00 00 00 00 00 00 00 00 00 00 00	until cols	RND+1 RND RND+1 MASK RSET	ENERN generation zero 20 9.X PDPULN population at least 510
** Gen random Oth gene STACK, PCR INIT ASK, PCR *PDATA+ Ask for seed *INCH+ get it from kbd RND CRLF begin randomize RND+1 *CRLF+ STACE FOR STACE STACE FOR STACE	Y CADDR 1, X RAND NEXTR 2, X X X X X X X X X X X X X X X X X X X	RAND XØ YØ COLLEN GO Until cols START GO TO IT RND		generation zero population at least
** Gen random Oth gene STACK, PCR INIT ASK, PCR *PDATA+ Ask for seed *INCH+ get it from kbd RND CRLF begin randomize RND+1 *CRLF+ STACE FOR STACE STACE FOR STACE	LDB Y@ CADDR CLBSR CADDR CLR ,X BSR RAND BEG NEXTR INC ,X INCA XØ STA XØ CMPA ROWLEN do until row #illed	RAND XØ YØ COLLEN GO Until cols START GO TO IT RND		LDX #0 STX GENERN seneration zero STX X0 LEAX 1,X STX POPULN POPUIAtion at least LDA #\$10 STA OFFS
240 EGU ** Gen random Øth gene 240 EAS STACK, PCR BSR INIT 253 LEAX ASK, PCR 260 JSR +PDATA+ Set it from kbd STA RND EDRA CRLF begin randomize 304 JSR +CRLF+	B4 LBSR CADDR CLR ,X BSR RAND BEG NEXTR INC ,X NEXTR INC ,X NEXTR INC ,X STAND STAND STAND STAND STAND STAND CMPA ROWLEN do until row #illed	BER RAND CLR XØ LDB YØ INCB YØ CMPB COLLEN do until cols BRA START GO TO IT LDA RND ASLA EORA RND	ASLA ROL ROL LDA ANDA RO CLRA RTS RSET COMA * RTS	LDX #0 STX GENERN seneration zero STX X0 LEAX 1.X STX POPULN Population at least LDA #\$10 STA OFFS

\$S-50 Computing


C3 Y1 X1 X1 X1 X1 X1 Y1 BBSE+1 BASE ADDR+1	D, PCR 4D, PCR	<u>*</u>	++ FA, Ø, 4	PE SOMETHING!" ROOM FOR STACK	ш
			TT (4 = 44)		I I
BPL ASRA BCS BCS BCS CDA CDA CDB ADDA STA	LDX LDD LEAX LEAX LEAY PSHS CLR INC	PSHS PSHS PSHS PSHS PSHS PSHS PSHS CMPX	BNE LEAS RTS FCC FCC FCC	MACRO FCC FCB ENDM TEXT TEXT	END
A FB C2 36 30 50 50 50 50 50 50 50 50 50 50 50 50 50			E4 62 28 20 20 20 04 00 04	TEXT * RSK * * SZF8 STACK	(S) DETECTED
21F9 2A 21F6 25 21FC 25 21FC 25 2200 06 2200 20 2204 96 2206 D6 2206 D8 2206 D9 2207 97 2207 97	2212 39 2213 50 2213 60 2215 30 2215 34 2221 05 2221 05	2225 24 2227 53 2229 34 2229 96 2220 88 2227 60 2233 35 2235 30	2239 26 2238 32 2230 39 223E 20 2260 20 2280 00	2284	Ø ERROR(S)
TABLE, PCR BASE TABLE1, PCR Y X+ clear the table X, s table end LP1 2.5 tidy stack 2.5 tidy stack 4*1B control chrs for Bantam **OUTCH* clear screen function ************************************	** ** ** ** ** ** ** ** ** ** ** ** **	#\$20 +0UTCH+ +0UTCH+ FOPULN, PCR POP +CRLF+ GENERN genern := genern # E	IN if populn = 0 seed 3554 IS4 IN PCR print upper border	TR4 	Print occupied cells
	↑0UTCH↓ * # #1B ↑0UTCH↓ * "H ← ↑0UTCH↓ GENERN, POP	##\$20 +00TCH+ +00TCH+ POPULN; POP +CRLF+ GENERN 1, X GENERN ##	FORULN CONT *WARMS* ROWLEN XØ LINE, PCR	*PLDATA+ CADDR FIRST * I * I * OUTCH* BLNK	PRINT MARK +OUTCH+ X0
LEAX STXX STXX CCRR CCRR BMF BMF LEAS RTS LDA LDA	JSR LDA JSR LEAX LEAX	LDA JSSR LEBSR JSSR LDX STEAX	CMPX BNE JMP LDX STX LEAX	JSR CLRB BRA JSR JSR LDA LDA	BEG LDA JSR DEC
ILP1 * START	* S. N		CONT CONT	RLOOP FIRST TSTCEL	PRINT
8D DF84 19 EF7E 20 EF7E 80 E64 FA FA 62 18 9F 0008	9F 0008 18 20CF 18 9F 0008 9F 0008 8D DF48 0131	56 0008 9F 0008 8D DF39 0120 9F 0004 27 01	25 04 9F 0010 16 2E 8D 012E	9F 000E 040 9F 0004 45 13 80	02 14 9F 0008 2E
200E 30 200B 3F 200B 34 200B 54 200B 6F 200B 20 20C3 39 20C3 86 20C3 86		2005.4 88 2005.8 AD 2005.8 AD 2005.7 AD 2005.7 AD 2005.7 SE 2005.8 AD 2005.8 AD 2005.8 AD 2005.8 AD 2005.8 AD 2005.8 AD		2118 AD 2115 AF 2115 SF 2115 5F 2119 20 2117 2118 AD 2121 AD 2121 AD 2121 AD 2121 AD 2121 AD 2121 AD 2121 AD 2121 AD	

15



6809 ASSEMBLY LANGUAGE PROGRAMMING

Lance A. Leventhal Osborne/McGraw-Hill



Review by Gary Manning

Having read several of Dr. Leventhal's books and even using a few as college texts, I have greatly appreciated his deep understanding of computer hardware and software. Occasionally though, I have felt that he was a bit too assuming on the reader's background. With this book however, I feel that the author has done a very good job of covering the subject thoroughly enough for the novice, and yet move quickly enough to keep the interest of those with programming experience.

The book has 21 chapters divided among four sections of from three to six chapters each, a fifth section on the instruction set, and five appendices. A comprehensive index is also included. The sections include:

Section I Fundamental Concepts 3 chapters - 82 pages

An introduction to computer languages, a discussion on assemblers, and an introduction to the 6809, its machine structure, instruction set, and addressing modes.

Section II Introductory Problems 6 chapters - 138 pages

Discusses problem solving and introduces simple load and store programs. Then advances through loops, coding and code conversion, arithmetic problems, and tables and lists.

Section III
Advanced Topics
6 chapters - 101 pages

Discusses subroutines, parameter passing, interrupts, and contains about 60 pages on using the 6820 PIA and 6850 ACIA.

Section IV Software Development 6 chapters - 101 pages

Includes problem definition, program design, debugging, testing, and maintenance and redesign. These discussions are informative yet concise and explain some advantages and disadvantages of the various techniques presented.

Section V
6809 Instruction Set
75 pages

Detailed information about each instruction.

Appendicies

A. Summary of the 6809 instruction set. 18 pages.

B. Summary of 6809 indexed and indirect addressing modes.

C. 6809 Instruction codes, memory requirements, and execution times. 4 pages.


D. 6809 instruction object codes in numerical order. 6 pages.

E. 6809 post bytes in numerical order. 1 Page.

The book has been printed with boldface type to present the material and lightface type to expand upon it. Another feature that I like is that the programming examples (there are 65 of them) are interesting and in many cases, even useful. This enhances the value of the book as a reference as well as a tutorial text. Also, problems are explained clearly and are not so difficult that they become frustrating. have found the book to be very useful and highly recommend it to anyone who does assembly language programming, or would like to learn.

[SS-50]

Now! Color for Your...



Introducing COLORAMA-50[™] Percom's SS-50 Bus Color VDG

eaturing ...


Eleven display formats including 8-color semigraphics, 4-color graphics, 2-color high density graphics and 2-color alphanumerics.

Moreover, two- and four-color displays may be switched between primary and complementary color sets under software control or from the keyboard.

Full graphic resolutions range from 64×64 picture elements to 256×192 picture elements.

Instant display control: The COLORAMA-50™ is memory mapped: your MPU has direct, instant access to display RAM and display control registers.

Low-cost Modulator Option for Color TV Interface: The COLO*RAM*A-50™ provides for installation of an inexpensive RF modulator such as Radio Shack PN 277-122 for operation using a color TV.



SS-50 Bus Department Store

Nobody supports the SS-50 bus like Percom:

- SS-50 Bus/Single-Board Computers with I/O ports & memory
- Static and Dynamic RAM cards memory expansion kits
- √ LFD-400/800 1-, 2- and 3-drive mini-disk systems
- Color and monochrome memory-mapped display controllers
- √ Extendable 7-slot SS-50 bus motherboards
- Versatile prototyping boards: SS-50 and SS-30 bus
- / Field-proven software: monitors, operating systems, drivers, editors, assemblers, debuggers and HLLs.

Mix in Sound: With the optional modulator installed, you can complement your colorful displays with software-controlled audio.



- Extended Addressing: The COLORAMA-50™ is compatible
 with the SS-5CA bus and the extended-address SS-50C bus.
 Map the board into any of the sixteen 64-Kbyte banks of the
 1-Mbyte SS-50C address space. The COLORAMA-50™ card
 "defaults" to the first (lowest) bank for the SS-50A bus.
- Cassettee I/O Option: Add a few.inexpensive components to the on-card circuitry provided and use an audio cassette for program/data storage.
- Provision for On-Card Firmware: Put your display operating system, cassette control program, etc. right on the COLORA-MA-50™ card in a 2516 (5-volt 2716) EPROM. Resides in the top 2-Kbyte of the card memory space.
- Operating Software: Included in the comprehensive users manual is a listing of a display operating system and cassette controller that may be implemented as a callable subroutine function from BASIC or existing operating systems. The programs are optionally available in a plug-in ROM for just \$69.95.

System Requirements

The COLORAMA-50™ is pin- and outline-compatible with the Percom System-50™ bus, the SS-50A (SS-50) bus and the SS-50C bus. The composite video-sync signal output will directly drive a color (or BW) video monitor. The output may be modulated for operation with a standard (NTSC) TV set. A modulator is not included. The COLORAMA-50™ card occupies 8-Kbytes of memory in the upper half of a 64-Kbyte memory space. Included on-card is 1-Kbyte of display RAM which will accommodate alphanumeric displays, semigraphic displays and two low-density full-graphic displays. For the higher density graphic displays, additional display RAM is required. The optional RAM ICs may be installed on the card.

For quality Percom SS-50 bus products, see your nearby authorized Percom dealer. To order direct, call **toll-free**, **1-800-527-1592**. Prices and specifications subject to change without notice. Prices do not include shipping and handling.

PERCOM DATA COMPANY, INC. 11220 PAGEMILL RD. DALLAS, TX 75243 (214) 340-7081

Toll-Free Order Number: 1-800-527-1222



Does timesharing on a small system make sense? It does with OS-9 Level One!

Now two (or more) acts can share your microcomputer stage. You will no longer have to walk away from your computer while it is busy running a long program. Because OS-9 is a multitasking operating system, you can be running a BASIC program while editing a PASCAL program, for example. This lets you make more efficient use of your time and your system, even if you only use one terminal. If your application requires multiple, independent terminals, one OS-9 system can do the work of several singleuser systems.

The convenience of an advanced operating system

Sophistication does not require complexity. Many OS-9 users say that it is actually easier to use than the older 6800-type operating systems. Consider how easy it is to run multiple programs: to run a program you just type its name and hit 'return.' To run a program as a separate job, you type its name, an '&' character, then hit return. The program runs as usual, but OS-9 comes back immediately and is ready for your next command. Simple commands let you see each program's status, set its priority, or abort it.

The file management system has fast, byteaddressable random-and sequential-access files. The tree-structured multiple directory system lets you create separate disk directories for each user, project, or application. Command line I/O file redirection means you specify what device and/or files a program will use when you run it, not when you write it.

Efficiency and hardware versatility

No other operating system can run on such a broad range of hardware: the overall RAM requirement for Level One is 32K to 56K RAM. Memory utilization is superlative because OS-9 lets multiple tasks "share" the same reentrant program. For example, if two users run BASICØ9, only one "copy" is actually loaded into memory. The Level Two version of OS-9 can utilize up to a megabyte of memory on systems having memory management hardware (both versions come with complete timesharing support).

OS-9's device independent I/O system can handle almost any number and combination of I/O devices: five or eight inch diskettes, winchester disks, disk cartridges, serial and parallel ports, memorymapped video displays, and more. Microware offers a large selection of "stock" device interface software modules, or you can create your own: all the information you need is in the manuals.

Excellent support and documentation

Each OS-9 package comes with a User's Manual and a System Programmer's Manual that cover every aspect of OS-9. If you have special requirements, you can even purchase the Source Code for most of OS-9 and related software. At Microware we take pride in offering the best customer support in the business. Technical advice and assistance by phone, mail or telex is available during all business hours.

Superb software tools

In addition to BASICØ9, Microware offers: PASCAL, Interactive Assembler, Macro Text Editor, Stylograph, Word Processor, Interactive Debugger, and coming soon, COBOL, and C language compilers.



Some people say BASIC 9 is really a PASCAL in disguise, others say it's still BASIC. You'll understand this delightful dilemma when you look at both versions of the "bubble sort" program shown below: both can be run by BASIC 99. The program on top is unstructured and hard to understand, but it's traditional BASIC. The program on the bottom is wellstructured and easy to follow, a virtue of PASCAL. With BASICØ9 you can program either way, or mix the best of both. It's like getting two languages for the price of one.

SORT AN ARRAY IN ASCENDING SEQUENCE

90 DIM A(5)

100 I=5

110 IF I=1 THEN 200

120 FOR J=1 TO I-1

130 IF $A(J) \le A(J+1)$ THEN 170

140 T = A(J+1)

150 A(J+1) = A(J)

160 A(J) = T

170 NEXT J

180 I=I-1

190 GOTO 110 200 RETURN

DIM array(5) outer=5

WHILE outer > 1 DO

outer = outer - 1

FOR inner=1 TO outer IF array(inner) > = array(inner + 1) THEN

temp = array(inner + 1)

array(inner + 1) = array(inner)

array(inner) = temp

ENDIF

NEXT inner

ENDWHILE

RETURN

Makes programs better

BASICØ9 has five kinds of loop structures: WHILE . . DO, REPEAT . . UNTIL, LOOP . . ENDLOOP, FOR . . NEXT and IF . . THEN . . ELSE. If one of the five built-in data types (byte, integer, real, string, and boolean) doesn't suit the problem, you can make a new one of your liking with the TYPE statement. Need a tree, linked list, or symbol table? Complex non-rectangular data structures using any combination of data types are easy to define. Modular programming breaks down large programs to smaller, more manageable elements. BASICØ9 or machine language recursion plus parameter passing to any other BASIC09 or machine language procedure. There is a complete set of statements for device-independent sequential or random I/O, plus a superlative PRINT USING system.

Makes programs faster

No full-feature BASIC for any 8-bit microprocessor is faster than BASICØ9, because it is an interactive compiler. As each program line is entered, it is instantly compiled to a smaller, faster form. Because BASICØ9 automatically converts programs back to original "source" form for listing, it is as friendly and easy-to-use as traditional interpreter BASICs. Each procedure can be independently compiled to position-independent, reentrant, ROMable format. Microware developed a new ultra-fast 9-digit-accuracy floating point math system just for BASICØ9. And if that's still not fast enough. there's BYTE and INTEGER arithmetic.

Features that make programs easier to write

The compiler is integrated with a

full-feature string AND line-number oriented text editor. If you make a mistake, BASICØ9 tells you instantly. String-oriented commands such as search, change, change all occurances, delete, and insert can be used on programs with or without line numbers. There's an automatic line renumbering function too.

Features that make programs easy to test

Debugging often takes longer than writing a program. That's why BASICØ9's integral high-level debugger sets it apart from all other compiled OR interpretive languages. The TRACE command shows you each statement executed in BASIC form, plus the result of any expression evaluation. STEP lets you run one or more statements at a time. LET and PRINT allow you to examine or change the values of variables, by name. STATE lists procedure calling order. And there are nine other debug commands. If you need to correct a program, you can edit, recompile, and rerun it in seconds.

Microware software is available for most popular 6809 computer systems.

Write or call for our free catalog. We accept phone orders and MasterCard and VISA orders.


OS-9 is a trademark of Microware. BASICØ9 is a trademark of Microware and Motorola.

MICROWARE. Microware Systems Corporation

5835 Grand Ave., Des Moines, IA 50312 (515) 279-8844 Telex 910-520-2535

OS-9 PASCAL:

A New Programming Tool For Experts



ISO-standard native code compiler? Microware's new OS-9 Pascal has all the features you need to handle the most demanding system and application programming tasks with ease.

Generates both native code and P-code

With OS-9 Pascal you don't have to make that difficult choice between easy-to-use P-code Pascal or fast native-code Pascal. You can compile your Pascal program to pure 6809 assembly language source code. OS-9 Pascal performs extensive local and global code optimization which results in incredibly fast and compact machine language programs. Or if you prefer. OS-9 Pascal can generate P-code for interpretive execution to simplify program debugging and testing. There's also a Virtual Memory P-code Interpreter that can run huge Pascal programs that other microcomputers can't touch. In fact, you can run programs using any combination of P-code, compiled machine language, or handwritten assembly language procedures.

ISO Standard Pascal Plus

OS-9 Pascal conforms to the ISO industry standard for Pascal, so you are assured of portability to or from any other computer that uses standard Pascal. OS-9 Pascal protects your software investment and gives you access to a vast body of existing Pascal software. Beyond the standard, we've added natural extensions to OS-9 Pascal to make it even more versatile. such as: relaxed identifier syntax; separate procedure compilation; random access file and interactive I/O: bitwise logical operators; runtime error handling; and much more. And because it runs under OS-9, it is inherently multiuser and multitasking.

A complete tool kit

OS-9 Pascal is a complete integrated Pascal environment for OS-9 that includes a comprehensive library of Pascal tools: a compiler, three P-code interpreters, a machine-language translator, linkage editor, cross-reference generator, and more. In short. everything you need for efficient, convenient Pascal programming.

It's available now

OS-9 Pascal is now available off-theshelf in all OS-9 disk formats. It can be used on any disk-based 6809 computer running OS-9 Level One or Level Two. Each OS-9 Pascal package includes the compiler, machine language translator, P-code interpreters, runtime support packages, linkage editor, demonstration programs, and a comprehensive 120-page User's Manual. Write or call for our free catalog. We accept phone orders and MasterCard and VISA orders.

OS-9 Pascal and OS-9 are trademarks of Microware.

Microware Systems Corporation 5835 Grand Ave., Des Moines, IA 50312 (515) 279-8844 Telex 910-520-2535

(Continued from page 5)

rmation about each device. Among other things this table contians, for each device, a byte indicating which bit(s) is the busy/ready bit and another byte indicating whether "ready" is a 1 or a 0. Changing this latter byte may be all that is required to get your printer working.

Jim Howell 5472 Playa Del Rey San Jose, CA 95123

Dear Jim,

I appreciate the letter, since I didn't answer all of your questions in the other article. I hope that this answer, along with the OS9 Exchange column will help.

Microware does not supply "instructions" for writing I/O drivers, and does not even supply source unless you purchase it. The one thing that you should remember, however, is that almost all of the existing software may be changed with the debug program to run the terminal, etc. to non-standard I/O addresses. The TMODE command is easily used to modify where the terminal resides and the protocol defaults. I'm sure that you will be able to perform these modifications once you have a copy that you can boot-up with. It may be that a standard system will have to be used to bring up the original version, and then make a modified "master" for you to use from then on.

As far as the file to automatically read commands from, this is already available and running with the "STARTUP" file. In fact, one disk I use boots up with BASIC09 as part of the "boot" and the modified modules along with it. At present, I don't use a particular application program often enough to boot directly into that, but it

surely is possible. The TMODE modifications or other module updates are possible to be loaded in with the STARTUP file or a new bootable disk may be made to include the newest modules as part of the boot.

We have received the source for the printer module to see if anything can be done to make the printer work, but so far, even with a lot of help from Microware we have not solved the printer hang-up. I can now make it print a line by pressing the feed button [which dumps the buffer], but it will not print by itself yet. We have come to the conclusion that the printer may need the modification, rather than the software.

Editor



30M BYTE 8-INCH WINCHESTER DRIVE

Smoke Signal Broadcasting, manufacturers of computer systems based on the 6800/6809 processors, has introduced the latest addition to the CHIEFTAIN Series of computer systems. Designated the CHIEFTAIN 98W30 this newest addition to the higher end of Smoke Signal Broadcasting's business computer line houses a 30 Megabyte 8-inch Winchester Disk Drive.

The new systems, the CHIEF-TAIN 98W30, is configured around the state-of-the-art 6809 microprocessor allowing programs to run at twice the speed of any other similar system. The excellent accuracy and speed of this 30 Megabyte drive, along with the DCB-4A Double Density Contro-

ller Board lends the CHIEFTAIN 98W30 a truly industry-standard title.

A wide range of programs are available for the CHIEFTAIN 98W30, including OS-9 Level I and Level II Multi-user, Multi-tasking Operating System. A standard CHIEFTAIN 98W30 incorporates 32K of RAM - expandable up to 1 Megabtye for specific requirements such as OS-9 Level II. The CHIEFTAIN 98W30 supports an 8-inch floppy disk drive for 1 Megabyte of back-up storage. A 20 Megabyte tape streamer option is also available.

The List Price for the CHIEFT-TAIN 98W30 is \$9995.00 and delivery is 30 to 45 days from order date.

CONTACT: Jim Allday, National Sales Manager or Deborah Conrad, Manager, Dealer Sales and Support, Smoke Signal Broadcasting, 31336 Via Colinas, Westlake Village, Ca. Telephone: (213) 889-9340.

SOFTWARE VENDOR DIRECTORY

The 5th Edition of the Software Vendor Directory by Micro-Serve, Inc. has just been published. As always it is a complete revision from the previous edition.

There are now over 1500 software vendors listed (Edition 4 had 1001). There are now 9000 software products listed (Edition 4 had 4000). There are 250 software categories listed (Edition 4 had 200). There are 110 hardware and operating system vendors indexed (Edition 4 had 80).

There are no game applications listed in the Directory. Product listings are limited to systems software, (operating systems, compilers, languages, data base managers, development tools, utilities, etc.) applications, (industry, business, professional, scientific, edu-

cational, etc.) plus catalogs books, and systems which support graphics, sound and plotters.

There are four sections to the Software Vendors Directory.

Edition 5 of the Software Vendor Directory is available at \$57.95 per copy or at \$100.00 for Edition 5 plus Editions 6 & 7 in March and October 1982 under the Subscription Service Plan.

Orders are accepted by telephone (914) 358-1340 or by writing

MICRO-SERVE, INC. P.O. Box 482 NYACK, NEW YORK 10960

SING 'N STEREO

Speech Systems, manufacturer of the Speak 'N Sing 1 and the Speak 'N Sing 2 speech synthesizers, is proud to announce the Sing 'N Stereo music and sound effects synthesizer. Each channel features an 8 bit D/A converter, seperate tone and volume controls, a low pass audio filter, and an on-board audio power amplifier that easily drives an external speaker.

Supplied software includes single and four voice music selections as well as several sound effects. Also included is a music compiler that allows one to easily develop single voice music. Available separately is a four voice stereo music compiler. The Sing 'N Stereo sound effects and music synthesizer is priced at \$69.95 and the ME-1 four voice stereo music compiler is available for \$39.95. All software is available in FLEX 2.0 or 9.0 formats and comes on 5¼ or 8 inch disks.

For further information call or write: Speech Systems, 38 W 255 Deerpath Road, Batavia, IL 60510, (312) 879-6880.

PRICES REDUCED

Harold Mauch, president of Percom Data Company, today announced major price reductions in the company's System-50 modules and devices.

Percom System-50 products are compatible with the SS-50 bus, a 50 pin bus supported by several manufacturers and used widely for 6800 and 6809 based personal computers.

Mauch said the new low prices are the result of decreasing chip prices and Percom's capacity for volume component purchases.

Mauch said the new low prices allow a person to get started in computing with an expandable, bus-oriented system for less than the cost of many one-board computers.

The SBC/9, a single-board computer/System-50 MPU card, now sells for \$139.95. The SBC/9 sold for \$199.95 before the new price announcement.

Percom's system-50 video display controllers, the *Electric Window* for black and white displays and the *Colorama-50* for color displays, have each been reduced \$80.00 to \$169.95 and \$139.95, respectively.

A Percom LFD mini-disk system, which includes four-drive controller, disk-operating system, the drive mechanism itself, inter-connecting cable and documentation, is now \$459.95, a reduction of \$140.00.

Prices of most other System-50 products, including memory cards, have also been substantially reduced.

Percom System-50 hardware, software and accessories may be ordered directly from Percom. The toll-free order number is 1-800-527-1222.

COMPUTERWARE'S PAC ATTACK

Computerware introduces its PAC ATTACK game on cassette for the Radio Shack Color Computer.

Computerware brings the fun of the arcades to your Color Computer with the new PAC ATTACK game. Three little muggers chase your man relentlessly around a maddening maze as you furiously try to build up points. This game's great graphics and sound effects offer continuous action at three levels of difficulty for computer buffs of all ages.

PAC ATTACK costs only \$24.95 plus \$2.00 SIH and is available directly from Computerware at Box 668, 1472 Encinitas Blvd., Encinitas, Ca. 92024, (714) - 436-3512.

COLOR COMPUTER BOARD

Compuware has introduced a new board that expands the memory of the Radio Shack Color Computer from 16K to 32K.

Computerware's 16 PLUS BO-ARD does not require soldering, plugs in easily, and fits neatly under the RF shield cover inside the computer. Complete installation instructions are included with the board.

Computerware's exclusive design allows the graphics display to reside anywhere within the 32K of memory. No software modifications are required for existing software and the 16 PLUS makes your Color Computer completely compatible with the anticipated disk systems.

The 16 PLUS BOARD costs only \$84.95 plus \$2.00 SIH and is available directly from Computerware at Box 668, 1472 Encinitas Blvd., Encinitas, CA 92024, phone (714) 436-3512.

[SS-50]



OS-9 EXCHANGE

By Ken Orme and Gary Manning

In a recent issue, we talked about BASIC09 and covered some of the features, timings and other phases. We will cover the random files this time, since most of the work that we have done has been with them.

BASIC09 has both sequential and random access files available. In order to use them, you must first CREATE a file. This BASIC allows you to create files with the word CREATE. The one thing that makes OS-9 slightly different from other BASIC's in the file department, is the use of a single file type that may be accessed either sequentially or at random. The files are expanded automatically by the PRINT, WRITE or PUT statements.

As with almost all other file handlers, you must OPEN an OS-9 file before you read or write from it. There are essentially three access modes to choose from; READ, WRITE, or UPDATE. Since the first two are self-explained, the last one means that it may be used to either READ or WRITE.

Since we are talking mostly about the random-access features of BASIC09, about all we need to remind you of with the sequential portion of the system is that it is about the same as all other sequential systems as far as access and handling are concerned.

However, data is stored in

sequential files in ASCII form with a carriage return as the record delimiter after each WRITE command. Data is retrieved from a sequential file by the READ command which returns a variable length record from the current file pointer to the next carriage return. The SEEK command is used to change the value of the file pointer and is usually only used with sequential files to perform the equivalent of a "rewind" (SEEK# path, 0). Since data in sequential files is stored in ASCII, it tends to be large and transfer is more slowly than in random files which use binary representation.

Data can be stored in random files as structures, elements of structures, or bytes. Since compputing the size of complex data structures can be very error-prone. a function called SIZE can be used which returns the size of any structure, array or variable. SIZE can be used in conjunction with SEEK to locate a specific record. SEEK#path, (N-1) \Rightarrow SIZE (names) would set the file pointer to the Nth record of a file called "Names". Data is written to a random file with the PUT statement and read by the GET statement. Since I/O devices are treated as files, files on magnetic media may be printed or displayed and updated via file transfers to or from the appropriate I/O device. Another nice feature is that as long

as there is available RAM, open files (or at least as much as will fit) will be kept in RAM until they are closed. This helps to avoid the mechanical wear and time delays of having to access the disk or tape for each read or write to a file.

The user's guide gives fairly good examples of the syntax and how to use the files. As with most manuals, this area leaves a little bit to be desired, however. The access to a random file is very fast as we have seen on program reading random files and displaying them at about 6 per second. Staying away from the "linked list" form of random access speeds things up and is very reliable.

OS9 VERIFY REPORT

Last issue I mentioned that the verify utility in version 1.1 may not be functioning properly. As it turns out, it was my thinking that was not functioning properly. I tried to use the verify the same way as version 1.0. However, the main difference is that verify assumes the standard input (terminal) and the standard output (terminal) unless modified. In order to verify a file named TEST and have it output to a file called TEST1, the following command should be entered: VERIFY TEST TEST1 U. The "U" tells verify to automatically update the file

CRC and header before writing the new file. Since the last article, we have used VERIFY many, many times and had it function properly. One of the tings that had us thinking it wasn't working is in version 1.0 you could verify a module in memory. With version 1.1 you must have the module saved first. The way to update or modify a module is to use Debug to modify it, save the module on disk, then use verify to update the program. You will most likely have to use the ATTR (attribute) command to change the file so you can execute it. Also, in order to insure that the newest version of a module is used is to change the version number (byte \$07) to a higher one. Then once the latest version is loaded into memory, it will be the one that will run. rather than the older version.

Interactive Debugger

Without the Debugger, those of you who desire to change or modify programs will feel as though you are handicapped. The Debugger is worth purchasing for anyone who works with OS9 more than casually. In a nutshell, it may be used for memory access, testing machine language programs, verifying memory and other such memory access tasks. It becomes for OS9 what a monitor program does for other disk operating systems.

One nice feature of OS9 is that the programs have prompts that let you know which one you are in. The Debugger is no exception, using "DB:" as the prompt. As with other programs, you may use upper or lower case characters. One of the most powerful features is the ability to interpret expressions. Most expressions may be written similar to those used in BASIC, with a few special operators and operands unique to the Debugger.

The operators available include addition, subtraction, multiplication, division, logical AND, logical OR, negate, and logical NOT. There are some special names for registers: Accumulator A, Accumulator B, Double Accumulator, X Register, Y Register, U Register, Direct Page Register, Stack Pointer, Program Computer, and the Condition Codes Register. Also used and a necessary part of the Debugger is "Dot", represented by ".". Dot is simply the debugger's current working address in memory. Typing "." will cause the current value of dot and the contents of that address to be displayed. Typing just a return increments Dot and prints its new value. To decrement dot, simply type a minus sign and a return. which decrements dot one step at a time. To change dot, you need only to type a period followed by an expression which is the new value of dot. To change the value in the memory location of dot. simply type an equals sign followed by an expression. The expression is evaluated and then the value of the expression is stored in dot. Also, if dot is changed, the last value of dot is saved and may be displayed by typing two periods.

The calculator mode may be entered by typing a space, followed by the expression to be calculated. In this mode, you may look at memory without changing dot, simulate 6809 indexed or indexed-indirect instructions. Conversion from decimal to hexidecimal, binary to hexidecimal and back may also be performed.

The register command allows you to examine one or all registers and change the register contents.

The breakpoint command allows you to set breakpoint addresses or to kill them.

Most programmers enjoy commands to display blocks of memory so that the porgram or

module may be displayed on the terminal or printer. Debug allows this function much like a monitor program. That is, by typing M followed by the starting and the ending addresses, the memory is displayed on screen with the hexidecimal values first and then the ASCII equivalent to the right. Two other commands are also quite useful. The search memory feature allows you to look for a one or two-byte value, beginning at your current (dot) location to the ending address specified. The third command performs a "walking bit" memory test between the addresses you specify. Any bit failing the test will be displayed.

There are several OS9 related commands available with the L or LINK command being the nicest one. With it, you are able to link to the module you specify in the command line. This saves a lot of time trying to find the module by simply advancing "dot" through memory. The dollar sign tells the Debugger to pass the rest of the command line to the shell, allowing such things as directory listing and utility programs to be run, returning to the debugger afterward. Also, by typing a \$ and then a return, you go back to the shell until an escape is entered, which then returns you to the debug program.

The execute command allows you to combine the debugger with a program, and even allows program execution by typing a "G".

Overall, there is little that the Debugger lacks in capability. About the only thing I really miss is a disassembler. It could be part of the Debugger or a seperate module, but would be a nice addition. If you purchase OS9, you will surely want and need the Debug program.

[SS-50]



Garland, Texas

No. 7

WHERE HAVE ALL THE COMPUTER KITS GONE?

by Harold Mauch

I like to visit computer stores and listen to the questions of customers.

Some ask about a common fruit; others ask about the health of a deceased gentleman from Fort Worth.

A few ask for a computer they can build themselves.

"I'm sorry," they're told, "but we don't carry kits any more. Too much hassle."

"If you like to experiment, we have a gee-whiz dandy Chroma Dazzler that can speak 16 languages, maintain 32,768 recipes, schedule 65,536 appointments and balance your checkbook.

And you don't even have to know how to program. We're offering this little gem today for just \$1,999.99, and that includes disk storage."

Just \$1,999.99?

Many a computerist bought a SWTP or other SS-50

CONTENTS

Where have the kits gone?	P1
Double-density for SS-50	P1
Of Interest	Р3
System Funriture	Р3
Microline-80 Printer	Р3

computer because of the processor. Or because they enjoy building kits. But I suspect more than a few bought kits because it was the one way they could afford to own a computer. No doubt there's a substantial market for computer kits. So why aren't there more computer kit manufacturers?

I think I know the answer.

The fine efforts of SWTP not withstanding, much System-50 hardware and software came out of the spare bedrooms, garages and basements of fledgling, but determined entrepreneurs.

Let's suppose you want to become just such an entrepreneur, and in the process maybe we'll find the answer to the question about the scarcity of kit yendors.

You decide to get into the computer kit business. Why kits? Well, you can't afford to start up an assembly operation. Besides, you honestly want to give prospective customers the lowest price possible. A

GENERAL INTEREST

Double-Density Adapter for System-50

Many people have asked if our double-denisty adapter, which we developed for the TRS-80☆ computer, could be used with the SS-50 bus disk controller. Unfortunately, it is not a simple plug-in-and-run situation for either the Percom or SWTP controller. However, the Doubler, as the Percom TRS-80☆ double-density adapter is called, can be easily connected to the older Smoke Signal controller. Dale French, one of our System-50 technical specialists, is working out the details for connecting the DOUBLERtm modifications along with the OS-9 driver in the next issue of the Peripheral.

price 15% above cost seems reasonable.

Design through hardware prototyping is easy. After all, you are a senior designer -- at TI no less. You do a little fine-tuning of the design and get prototypes made. Now the fun begins.

A small ad in Byte and a small stock of kit parts wipes out most of the family savings. You confidently reassure your wife, however, and together you wait for the orders to roll in.

Meanwhile, you hawk a few kits to members of the local computer club. And spend the next several weeks solving their individual problems -- cold solder joints, wrong capacitor polarities and owner design "Improvements" that don't work.

Finally your ad appears in Byte. You soar like an eagle. (Hon, we're gonna be rich!)

You resist the urge to buy up all the new Byte magazines at the local computer store, limiting yourself to a mere 10 copies. Of course mother back in Toledo gets one. (Look Ma, I've got my own business!

The Byte ad makes you an instant expert, so naturally you're invited to give a demo at the next computer club meeting. Is this the beginning of fame?

By now the ad has been out a week. You've had a few callers (keep that damn dog quiet while I'm on the phone!), and a few people have written for more information. (*More* information? Good grief, the ad copy took two days to write and gives everything but the length of the heat sink bolts.)

Never mind. You take the Byte ad, and with the help of your wife's thesaurus, grind out a data sheet. You include specifications for the heat sink fastener.

Before long the postman is delivering your bills in a basket: an invoice for the data sheet printing, a Byte invoice for the next ad insertion, a phone bill that infuriates your wife (Hon, call the phone company, I know I didn't make that many long-distance phone calls.), and so on.

Your boss at TI is beginning to make snide remarks about the lagging status of your work project. But these are trifles compared to the next bomb?: a design flaw in the kit! (Oh, my God! How can I face the computer club again.)

You design out the flaw but can't ship because the new IC for the fix isn't available. The complaints begin. "Whereinhell's my kit -- you promised it four weeks ago."

One irate customer wants his money back. Another demands to know why the users manual doesn't explain how to use the product with his home brew 4004 machine. Both promise scathing letters to Byte, the Better Business Bureau and their congressmen. (God, my gut aches.)

The new ICs finally arrive. Your wife calls you at work to tell you the UPS driver won't take a personal check. (Cashier's check or money order, please.)

You tell the boss that son #2 seems to be having an attack of appendicitis, and must be rushed to the hospital. Than you rush to the bank, withdraw \$475 from the wife's Christmas Club account and race to the house. Wife suspects, but you jump back in the car before the questions start. Back at work you tell the boss it was a false alarm, "The little nipper just ate too many fresh cherries, heh, heh."

More than a few long-distance callers, saying they weren't about to buy a pig-in-a-poke, want to know the whereabouts of dealers in their area. So you decide to line up dealers.

The first dealer doesn't have the courtesy to say goodbye when you suggest a dealer cost of 5% off retail. Neither does the second dealer, the third, etc. You soon learn that retailers expect--indeed need-- a 35% mark up. Or thereabouts.

You call an old college friend, one who switched from engineering to a business major, and plead your case. After he stops laughing (why did I tell him we price at 15% above costs), and after discussing cash flow and return on investment, he offers to help -- for a piece of the action. (Maybe these business majors are really the smart ones after all?)

At any rate you raise the price and start calling dealers again. Now the price is OK, but the dealers won't carry kits: too much hassle. (No fools, these dealers.) So willy-nilly, you get into the business of assembling electronic modules. You start slow. Boy, do you start slow -- one employee, an ex-TI assembler needing part time work, a soldering iron and flux, a solder sucker and a few hand tools. The lady assember is competent: her only question concerns getting paid. Nothing serious.

In the unlikely event (as you tell yourself) that you can't "meet payroll," you decide to seek a bank loan. Bankers make unsecured loans about as often as smog-free days occur in Los Angeles, so you pledge your car, the house, a quart of blood and a pound of fleshbut get the loan.

You meet the payroll, i.e., you pay the lady assembler. She smiles, looks at the check, frowns, shrugs and disappears forever. You're out of the assembly business.

It's time, you decide, to sit down and take a real hard look at the business. You call a buddy, a fellow industrialist of kindred interests, and together do a (sound of bugles, roll of drums) COST ANALYSIS. All things considered -- parts bagging errors, solder bridges, troubleshooting over the telephone and letters, letters, letters -- you conclude that...

Kits cost more!

And that, weary reader, is the bottom line. It costs more to produce, market and support kits (with the

emphasis on support) than it costs to produce and sell assembled and tested units.

It is enlightening, in this respect, to compare the price of a Heathkit color TV kit to the price of a comparable RCA, Magnavox or Quasar set. There's little difference. Yet, the customer will always insist that kits be priced substantially lower.

Unfortunately -- for those of us who would rather build a kit -- few kit suppliers become very successful. And it appears that we will be getting those few kits that are available from a UPS delivery man, after placing a long-distance call that's answered from a phone in a bedroom or garage.

OF INTEREST -- Harold Mauch, president of Percom Data Company, recently announced that Percom and Access Unlimited, a computer retailer, have agreed to join in a cooperative venture which will make Access Unlimited a retailer of Percom System-50 (SS-50) products.

Access Unlimited is a Richardson, Texas-based mail-order and direct sales retailer of computer-equipment, software and parts.

Manufacturers and software vendors other than Percom also will be contacted.

The program calls for Access to become one of the largest, if not the largest, integrated, full-line source of 680X products for the sophisticated System-50 market place.

Interested suppliers can reach Access Unlimited at:
401 N. Central Expressway #600
Richardson, Texas 75080
(214) 690-0206

NEW PRODUCTS

Although this section usually features new System-50 hardware and software products, in this issue we would like to mention two computing "Accessory" items that we have carried for only a short time but which are proving to be very popular.



System Desk, Printer Stand --Custom-designed to Percom specifications, this system of low-cost computer

furniture organizes your computer station into a compact, convenient arrangement of accessories and peripherals.

- ☆ Furniture quality styling and finish.
- ☆ Modular design lets you customize to paricular needs.
- ☆ Units knock down for shipment -- delivery is right to your door.
- ☆ Snap-locking fasteners -- no tools required for reassembly.

System Desk

The under-desk module accommodates either one or two drawers, and can be located either to the right or to the left. The drawers, which are on ball-bearing rollers, have a full-width opening in the rear for equipment cabling.

The riser shelf can be used to support a display unit, hold reference manuals, etc. The riser also can be positioned either to the left or to the right.

Printer Stand

The under-desk module plays a dual role, serving either as the desk bay or, with an optional top added, as a printer stand. With the top in place, the printer stand and desk are the same height.

Specifications --The desk is 48" wide, 24" deep and 26-½" high (typing height). The riser is 23" wide and 11" deep. The riser shelf can be at 7-½" or 11" above the desk top. The desk bay inside dimensions are 16" wide by 16" deep by 10½" clearance height. The printer stand (under-desk module with top in place) is 24" wide by 24" deep by 26-½" high. Finish is wood and durable plastic laminate.

To order or for additional literature, call toll-free 1-800-527-1222.



Microline 80 Printer

No other serial dot-matrix printer has so many features for the price:

- Prints upper and lower case characters standard-condensed- and double-width faces.
- ☆ Prints block graphic characters.
- Alphanumeric characters are in easy-to-read 9x6-dot matrix format; graphic characters are 6x12 dot.
- ☆ Font selection and line spacing are programmable.
- ☆ Prints 80 cps with no duty cycle limitation.
- ☆ Print head is warranted for 200,000,000 impressions the equivalent of over nine years of microcomputing ☆ Handles cut sheets, roll paper and fan-fold pin-feed

stock. Optional snap-on tractors are available for other forms

☆ Standard interface is parallel, Centronics compatible. Optional serial interface available.

☆ The Microline 80 is rugged (cast aluminum base), lightweight, quiet and dependable. And inexpensive.

To order or for additional literature, call toll-free 1-800-527-1222.

Editors Note-

A supplement to the Peripheral is available from Percom Data Company. The supplement includes more specific information - - for example, additional notes on product improvement and maintenance. This supplement may be obtained from Percom by calling our toll-free order number, 1-800-527-1222. From within Texas, call (214) 340-7081.

TRADEMARKS APPEARING IN THIS ISSUE OF THE PERIPHERAL:

PERCOM is a trademark of Percom Data Company,

TRS-80 is a trademark of Tandy Radio Shack Corporation which has no relationship to Percom Data Company.

BE SURE TO MENTION SS-50 COMPUTING WHEN CONTACTING **ADVERTISERS**

SS-50 Bookstore

6809 Assembly Language Programming This book presents a thorough introduction to assembly language programming and a complete discussion of the 6809 instruction set. It starts at a very basic level and builds into actual programming techniques, I/O structures, and hardware interfaces. Lance Leventhal. 530 pages. Order No. 357 \$16.99



6809 Microcomputer Programming and Interfacing/Experiments



This book is written to give sound information on how to program and interface the 6809-the high performance 8-bit microprocessor. It contains seven chapters and four appendices and is valuable as a "cookbook" aid when working with the 6809. By Andrew Staugaard, Jr. - 304 pages - Order No. 21798 \$13.95

68000 Microprocessor Handbook

This handbook gives a complete comprehensive picture of the 16 bit 68000 microprocessor, its timing, and special features. Also, several practical application problems and discussed and it is compared to other 16 bit devices. By Adam Osborne - 220 pages. Order No. 411 \$6.99




MC6809

MC6809 Cookbook

This cookbook explains the basic operation of the 6809 and the 6809E microprocessors. Everything from the timing and clock information to the instruction set are covered. By Carl D. Warren - Order No. 1209 \$6.95

Orders should include title and order no., along with check, m.o., or VISA -Master Card info. - Mail to: SS-50 Computing Bookstore, P.O. Box 398, Garland, UT 84312. Include \$1.50 per book for shipping and handling. Please allow for personal checks to Sorry, no COD's. Foreign orders should include \$7.00 per book shipping.

Model 6800CL4 CalClock/TIMER



IT'S A HARDWARE CALENDAR/CLOCK

- Keeps date and time without servicing by the computer
- Day-of-week, month/day/year, hour:min:sec (12/24hr.+ auto Leap Year)
- Hands off setting/control/access of ALL functions via software
- On-card battery and charging circuit keeps time for months, power off

WITH AN INTERVAL TIMER INCLUDED

• For (TSC/Flex 2/9 compatible) printer spooling, multi-tasking, etc.

Fully assembled & tested* \$99.95 5" Disk (Flex2 🗆 Flex9 🔲) \$10.00 Complete kit* \$69.95 Goldplated buss connectors \$6.00 Shipping & handling \$3.00

* FULLY DOCUMENTED: instructions; diagrams; theory; more than 20 pages of sample software (automatically puts date in Flex2/9[®] date buffer, adds time-of-day to assembly listings, maintains constant, current time+date display on top line of CRT). Batteries not included. All IC's socketed.

© FLEX is the registered trademark of Technical Systems Consultants, Inc.



COMPUWARE Corporation P.O. Box 2710 Cherry Hill, NJ 08003 609-428-2309 Dealer and Volume Discounts Available

New Jersey buyers: ADD 5% Terms: CASH; MC; or Visa Flex9[®] Flex2[®] (default)

TEXAS COMPUTER

TG-1 BIT RATE GENERATOR

- Supplies 9 standard bit rates from 19.2k to 110 simultaneously, which is not possible with any circuit using a MC14411 chip
- Uses no parts from your present system
- Requires no additional upgrade parts for MPA or MPA-2 boards
- Facilitates upgrading to SS50C status
- Gold plated connectors are standard on all JEXAS COMPUTER products
- COMPLETE AND TESTED WITH DOCUMENTATION \$49.00

DPB DUAL PORT SERIAL BOARD

- Compatabile with both SS30 & SS30-C
- Full RTS, DCD, CTS etc. jumper control
- Top mount baud rate switches for easy access
- Two DB25 connectors for easy hookup
- Easily modified for separate xmit/recv clocks
- COMPLETE AND TESTED WITH DOCUMENTATION \$69.00

add for shipping \$3.00

P.O. BOX 120816 ARLINGTON, TX 76012

VISA/ MC

817-275-1848

POWERFUL COLOR GRAPHICS

Uses the new TMS 9918A Video Display Processor High resolution 256×192 pixel display with fifteen colors 16k Bytes of onboard dynamic 150nS RAM included 32 graphic images can be individually moved with single

X-Y command for smooth animation External video input allows subtitling

SOUND EFFECTS AND MUSIC

Three AY3-8910 Programmable Sound Generators Nine simultaneous voices Three independent noise sources Onboard stereo amplifiers drive two speakers


SOFTWARE AND DOCUMENTATION

Programming manuals for Video and Sound Processors Subroutine library and demonstration game Software in both BASIC and 6809 assembly

ADDITIONAL I/O CAPABILITIES

Eight analog inputs with 8 bit resolution Supports four joysticks with pushbutton switches Eight bit port for ASCII or organ keyboard Maps into any 256 bytes of memory

ARCADE 50



ARCADE 50, assembled and tested video and audio connector set 15. 4 joystick connector set (5 pin DIN) 20. 2 Radio Shack joysticks 24. UHF modulator 32. gold molex 12.

LAB VIDEO (EXORciser° version) 1st quarter '82

specify 5" or 8" TSC's FLEX compatible disk terms: cash, VISA, M C or C.O.D. overseas orders add \$20

(° Trademark of MOTOROLA INC.)

TERMINUS DESIGN INC 16 Scarbrough Road Ellenwood GA 30049 (404) 474-4866

STYLOGRAPH

6809 WORD PROCESSING SYSTEM

STYLOGRAPH 2.0

All of the convenience and features for which Stylograph is well known plus:

- True proportional printing on specialty printers.
- Files longer than memory.
- "Help" command to aid in learning.
- New menu driven, self prompting functions.
- Left and right scrolling for pages larger than screen.
- Embedded printer control commands allowed.
- Simplified method for underline, boldface, superscript, etc.
- Supports NEC, Diablo, Qume, 737, and 739 printers.
- Can be user configured for virtually any terminal or printer.

\$295, manual \$15, updates from old versions \$180.

STYLOGRAPH 3.0

This version is designed for "tty" printers but is otherwise identical to version two. It does not support specialty characteristics such as superscript, subscript, incremental printing, and proportional printing.

\$195, manual \$15, updates from old versions \$90.

STYLOGRAPH MAIL MERGE

This program takes files of variables, such as names and addresses, and inserts them into a Stylograph text file for automated mail list generation. It will also allow a number of Stylograph text files to be appended at printout time so that page numbers and headings will be continuous in the printout.

\$125, manual \$10.

STYLOGRAPH SPELLING CHECKER

This is a valuable addition to any word processing application. It checks all words in a manuscript against an internal dictionary. The dictionary included has a vocabulary of over 20,000 words and is fully expandable. New words encountered in the text may be added to the dictionary making the creation of custom tailored and foreign language dictionaries a snap.

\$145, manual \$10.

When ordering specify operating system (FLEXTM, UniflexTM, or OS- 9^{TM}) and disk size. VISA & MC accepted. 20% discount on 3 program order.



STYLO SYSTEMSBOX 238 WILLIAMSVILLE, NY 14221 **716—634-2466**



Now your 6800 or 6809 system can proof-read your text files and fix your spelling and typographical errors in just minutes.

MAGIC SPELL® compares each word in your file against a dictionary, displays or prints every word not found, and lets you correct it on the spot. The result is an error-free text within minutes.

MAGIC SPELL® is written for the non-technical user. It has several options, including listing to a terminal or printer, correcting or marking errors, adding new words to the dictionary, or generating a custom dictionary to fit your writing sytle. Although it comes with a complete manual which explains every option in plain language, MAGIC SPELL prompts for all the information it needs so even beginners can use it without constantly referring to the manual.

MAGIC SPELL[®] is extremely fast and compact. It will run in systems as small as 16K, can correct documents up to ten times larger than available memory, and reads text at a rate of about ten pages per minute. MAGIC SPELL[®] is in stock now for Technical Systems Consultants' MiniFlex, 6800 Flex, and 6809 Flex, as well as for Percom Disk systems. OS-9 and SSB versions will be available soon. It is available in two versions:

MAGIC SPELL I is for the general user. It comes with a 10,000 word dictionary, and costs \$89.29. This is the version we ourselves use.


MAGIC SPELL II is for the professional writer who demands the very best. It contains several speed enhancements, and features a 75,000 word dictionary. This version is available only for 6809 systems, and costs \$239.29.

STAR-KITS

P.O. BOX 209

MT. KISCO, NEW YORK 10549

(914) 241-0287



- Supports the 6801 microcomputer family
- Only 4x6%" including a 4x2" prototyping area
 - 2K Bytes EPROM/2K Bytes RAM/RS-232 Interface
- Complete documentation (over 50 pages)

MC6801 APPLICATIONS PROTOTYPE BOARD

The APB is a small board whici, supports the MC6801 family of microcomputers. It is described in Motorola's application note AN799. A typical 6801 member contains an enhanced 6800 processor, 2K bytes of ROM, 128 bytes of RAM, a 16-bit programmable timer, parallel I/O, and a serial communications interface. In addition to the resources of the 6801, the APB provides an additional 2K bytes of EPROM (TMS2716), 2K bytes of RAM (2114L), and a full duplex RS-232 interface. It also supports special versions such as the 6801G1 with its LILbug* monitor; and provides on-board programming of the 68701 EPROM version.

The APB is an excellent educational aid which allows for evaluation and familiarization

The APB is an excellent **educational aid** which allows for evaluation and familiarization of 6801 family members . . . It is great for **prototype development**. Since the 'nuts and bolts' are already in place, the designer need only add the necessary interface circuits for a particular application . . It can also be used as a simple cost-effective **dedicated controller** for those limited quantity applications.

Besides being so practical, it is a fun little board. Order yours today!

* TM of Motorola Semiconductor Products, Inc.

APB-1 Bare board with documentation \$19

APB-2 Above assembled with all parts less microcomputer and memory \$69

APB-3 Above with MC6801G1 and LILbug manual \$109

APB-4 Above with four 2114L RAMs. \$129

For the SS-30 Bus:

AD-68A A/D Converter - 8 channels, 8 bit, 0-2.5V input, 6ms conversion time — \$39 A&T CI-68A Control Interface - 8 opto-isolated inputs, 8 reed relay outputs — \$79 kit, \$98 A&T

Terms: Check, MO, VISA, or MC. In US and Canada add \$3 per item for shipping. Others add \$7 per item. US funds only. TX add 5% tax. Shipped from stock to two weeks.



INNOVATIVE TECHNOLOGY 510 Oxford Park Garland, TX 75043 (214) 270-8393


6809

RECORD MANAGEMENT SYSTEM

RMS

DATABASE MANAGEMENT

- •USER DEFINED RECORD FORMAT VIA DATA DICTIONARY
- •SCREEN ORIENTED, FORM FILL OUT TYPE OF ACCESS
- **OPTIONAL TWO LEVEL RECORD HIERARCHY**
- •ALL FILES IN ASCII TEXT FORMAT, BASIC COMPATIBLE
- •DIRECT ACCESS BY KEY FIELD, MULTIPLE INDEX FILES
- •EXTENSIVE DOCUMENTATION, SAMPLE APPLICATION
- •VERSATILE, PROFESSIONAL QUALITY REPORT WRITER
- •BUILT-IN SORT/MERGE
- •EASY TO USE



RMS is a complete DATABASE MANAGEMENT package for the 6809 computer. It is made up of five machine language programs that make up the most powerful business programming tool available for the 6809. It can be used by the relative novice, to implement an incredible variety of information storage and retrieval applications, without any programming. However, the programmer can use RMS as part of the solution to a larger problem, saving many hours of unnecessary program development time. RMS can be used to handle data input, editing, validation, on-line retrieval, sorting and printed reports. Custom data manipulation can be filled in by the user's BASIC programs.

SINGLE CPU LICENSE

FLEX* \$200 OS-9+ \$250 UNIFLEX* \$300

TERMS: VISA / MC / PREPAID

WASHINGTON COMPUTER SERVICES

3028 SILVERN LANE BELLINGHAM, WA 98225 1 (206) 734-8248

* FLEX and UNIFLEX are trademarks of Technical System Consultants Inc.; + OS-9 is a trademark of Microware

SUPER SLEUTH

DISASSEMBLERS for 6800/1/9

- -analyze (6800/1/5/9&6502) or (Z-80,8080/5)
- -easy-to-use, with extensive manual
- -includes xref and name-changer EACH \$99

CROSS-ASSEMBLERS

MACRO SETS for TSC 6809 ASSEMBLER

-generate code for 6800/1,6805,6502,Z-80,8080/5 EACH \$50,ANY 3 \$100

DEBUGGING SIMULATORS

RUN on 6800/1/9

- -easy-to-use, with extensive manual
- -for 6805
- -for 6502

EACH \$75

Telephone 404-483-1717/4570

For catalog or dealer information contact Bud Pass
Exclusive U. K. dealer is Compusense in London

TABULA RASA

FULL-SCREEN ELECTRONIC

SPREADSHEET SYSTEM

-similar to DESKTOP/PLAN

(TM Desktop Computing)

\$100

6502 TRANSLATOR

- -translates 6502 source to 6809 source
- -easy-to-use, with comprehensive manual

\$75 (coming)

FULL-SCREEN DISPLAY

FOR XBASIC on 6809, uses terminals and video boards

- -forms display generator \$50
- -mailing-list system (menu-driven, powerful) \$100
- -inventory and manufacturing \$100

TSC BASIC UTILITIES

- -xref and resequencer for BASIC, XBASIC, PC, XPC \$25
- -sort-merge XPC program generator \$25

ONLY YOU CAN STOP SOFTWARE PIRACY!

All programs run under 6809 FLEX – some also run on 6800/1

CALL ABOUT UNIFLEX VERSIONS OF PROGRAMS

(UNI) FLEX trademark Technical Systems Consultants


All programs provided in source on disk – specify 5"/8", density, sides

For VISA and MASTER CARD give account, exp. date, phone U. S. funds only -- add 5% (10% overseas) for shipping

Open P. O.'s for D&B rated clients only

It's available

D64KB - 64K Dynamic Memory Board



For The SS-50/SS-50C Bus

- Completely TRANSPARENT Refresh [During 01] at 1 MHz
- Operates with BOTH 6800 and 6809 systems
- Compatible with the 20 bit extended addressing mode.
- Diode Protection On The -5V Power Line
- Memory Selection and Relocation For Testing
- LOW POWER 12V at 150 mA 5V at 500 mA -5V at 7 mA
- 4116 Type RAM With 200 ns Access Time
- Printed Circuit Board:
 Double Sided With Plated-Through Holes
 Silkscreen Component Layout On Top Side
 Solder Mask On Bottom Side
 9 inches by 5.8 inches
- Designed around Motorola MC3242A and MC3480 Delay Lines To Ensure:
- NO Timing or Temperature Problems
- NO [NONE] One-Shots
- NO Adjustments

PRICES

OPTION 1 - \$80.00 Includes PC Board and 18 Pages of Documentation.

OPTION 2 - \$100.00 Same as Option 1 plus Delay Lines

OPTION 3 - \$120.00 Same as Option 2 Plus the Two Memory Contollers

OPTION 4 - \$210.00 Same as option 3 Plus all other TTL chips [Full Kit, less memory]

OPTION 5 - \$250.00 Completely Assembled and Tested but Without 4116's

BOAZ Co. Box 18081 San Jose, Ca. 95158

PHONE [408] 269-9522

Also available - Extender Boards from BOAZ 50 Pin Board - \$15.00

30 Pin Board - \$12.00

Orders Should Include \$5.00 Shipping
California residents add 6 1/2% Sales Tax
Cash - Check - Money Order

(Allow 3-4 weeks for personal checks to clear)

word's worth

P.O. Box 28954 Dallas, Texas 75228

C COMPILER FOR 6809

Based on SMALL-C as published in Dr. Dobbs by Ron Cain. Transported to DOS69D by Allan Batteiger, adapted to FLEX by Bill Knight. FLEX version requires a special loader (included). Current plans are to produce a full Courrent plans are to produce a full Course to produce a full Courrent plans are to produce a full Courrent plans are to produce a full Courrent plans are to produce a full Course to produce in three steps: Ver. 1.0 available now; ver. 2.0 - 2nd Q/82; ver. 3.0 - 4th Q/82. Prices to be announced. Liberal upgrade policy. User's for compiler, library. guide, binary and for run-time source 48K system recommended.

For FLEX 9.0 (with loader) \$52.50 For DOS69D \$47.50

RLOAD 3.Ø

Relocating linking loader for TSC's absolute assembler. Enhanced version of RLOAD published in '68' Micro Journal by HL Harkness. Source and documentation on the disk.

RLOAD for FLEX 9.0

\$17.50

FIG-FORTH FOR FLEX 9.0


FIG does not supply machine-readable source to their otherwise excellent package. Two disks - (1) Source in FLEX format, (2) FORTH editor published in Forth Dimensions, ('screen' disk). Supplied without comments, except for a few minor bug fixes. Intended to supplement, not replace, the FIG-supplied documentation. Saves about 10 hours of typing. SSB version to be announced.

FORTH for FLEX 9.0 (2 disks) \$19.50

These programs normally supplied on 5" disk. For 8", add \$2.00 per disk. Prices good until February '82. Shipping and handling included. Texas residents: add \$0.25 sales tax per 5" disk, \$0.35 per 8" disk. Specify operating system and disk size. Visa and MasterCard prices 5% higher. Allow 4 weeks for check. Please do not send cash through the mail.

DOS69D is a trademark of Smoke Signal Broadcasting. FLEX is a trademark of Technical Systems Consultants. FIG stands for the FORTH Interest Group.

STAR-KITS



6800 HARDWARE

SBC-02 single board computer uses 6802 with RAM, ROM, I/O. Ideal controller, intelligent interface, and more. Printed circuit board is \$25, complete controller kit \$75, wired and tested \$150. Also available: HUMBUG (see below), Basic in ROM, etc.

CT-PS serial/parallel interface card. ACIA-type interface for RS-232C terminal and/or a parallel keyboard. Makes keyboard look like a terminal with absolutely no program patching. Ideal for video board based systems. Bare board \$20, complete kit \$55, wired \$100.

6800 AND 6809 FIRMWARE

6800 HUMBUG monitor. Totally MIKBUG compatible, plus single-stepping, multiple breakpoints, formatted memory dumps, multiple port control and more. "Fantastic!" say our customers. 2K version \$40 on 2708 or 2716 EPROM with source listing. Alternate versions, including video board versions available.

6809 HUMBUG-09 has all the features of 6800 HUMBUG and more. Not just a compatible monitor, but a debugging package and system I/O manager as well. Two ROMs, manual and full program listing for \$75. Also available in video board versions.

6800 AND 6809 SOFTWARE

BASIC UTILITY PACKAGE renumbers, pretty-prints, prints variable and transfer indexes, compares, shortens Basic programs. On Percom or miniFlex* disk for \$30.

CHECK 'N TAX balances your checkbook, finds errors, prepares income tax data. On Percom, miniFlex*, Flex 2.0* or Flex 9* disk for \$40.

SORT-MERGE—the only one for Percom disk systems, sorts even full-disk files. \$35.

NEWTALK for your 6800 or 6809 system makes it talk to you. This memory dump utility outputs through a music board or any PIA port. \$30 on Percom or Flex 2/9 disk, or cassette.

6800 CROSS-ASSEMBLER written in Basic. Assemble 6800/6802 programs on your new 6809 (or your 370 at work!). Available on 5" disk, KC cassette, or TRS-80 Level II cassette for \$9.95.

GAME PACK with Eliza and 3-D Tic-Tac-Toe. 5" disk or KC cassette \$15.

Send s.a.s.e. for catalog. For detailed information, buy any manual for \$5 and get \$6 credit toward purchase. (* is a trademark of Technical Systems Consultants.)

STAR-KITS, P.O. Box 209, Mt. Kisco NY 10549

THOMAS INSTRUMENTATION

THE MACHINE TOOL, INDUSTRIAL SPECIALISTS IN BUSINESS ON A **FULL TIME BASIS FOR 10 YEARS**

NEW PRODUCT:

S-R/R

48K 2MHz STATIC RAM/ROM CARD

*24 2K blocks memory mapped on any 2K boundary

*uses low power 2016P-2 (2128) RAM and/or 2716 ROM

*mix 4K blocks of RAM and ROM

*6800 and 6809 compatible

*use on SS-50 and SS-50C buss

*decoded for extended addressing

*5 volts only

*low power consumption (typ. ½ amp with 48K RAM)

*gold connectors

Bare Board \$49.00 2716 1MHZ \$9.95 2016 P-2 2MHZ \$16.50

A/T with 16K \$250.00; with 32K \$375.00; with 48K \$495.00

A/T without memory chips \$120.00

NEW ACCESSORIES FOR 68XX USERS:

SS-50/SS-50C EXTENDER CARD SS-30 EXTENDER CARD

\$35.00 \$25.00

*Both cards assembled with a built in logic aid & gold edge connectors SS-30 WIRE-WRAP/PROTOTYPE BOARD (board only)

\$20.00

*Pad spacing permits most standard sockets from 8 to 64 pins

*Provision has been made for voltage regulators

FEATURED PRODUCT:

SP-1 Bare card \$49.00 Asm. + tested \$195.00

*A super prototype board

*Card design includes

(3) 6821(4) 6850

6 parallel ports 4 serial ports

(1) 6840

3 16 bit counter/timers

which are fully buffered and decoded

*Accomodates a mix of 38, 14 & 16 pin wire wrap sockets

cing permits	most standard sockets from 8 to 64 pins	
\$ 49.00		
\$195.00		\$395.00
\$325.00		\$ 10.00
	BACKPLANES AND MOTHERBOARDS	
\$235.00	*16 position SS-50	\$80.00
\$ 29.00	*12 position SS-50	\$60.00
\$ 59.00	* 8 position SS-50	\$40.00
\$195.00		\$30.00
\$ 49.00		\$20.00
	* 8 position SS-30	\$39.00
\$139.00	**Commentance	
	GULD \$1.00 ea. (M or F)	
	111N M 5.40 ea. F 5.50 ea.	
1.0		
	\$ 49.00 \$195.00 \$325.00 \$235.00 \$ 29.00 \$ 59.00 \$195.00	\$195.00 A/T with extra features \$325.00 Software obj. & src. on FLEX disk BACKPLANES AND MOTHERBOARDS \$235.00 *16 position SS-50 \$ 29.00 *12 position SS-50 \$ 59.00 *8 position SS-50 \$ 195.00 *6 position SS-50 \$ 49.00 *4 position SS-50 *8 position SS-30 \$139.00 **Connectors: \$ 49.00 GOLD \$1.60 ea. (M or F) \$ 39.00 \$ 95.00

DEALERS FOR SWIPC, GIMIX, AND TSC

*All Thomas Instrumentation's cards come with full documentation including software source listings where applicable *All assembled cards are burned in at 150F and fully tested with Gold conn. *Bare card prices do not include edge connectors *See previous ads, write, or call for more detailed information.

THOMAS INSTRUMENTATION

168 EIGHTH STREET — AVALON, N.J. 08202 (609) 967-4280 NJ RES. INCLUDE 5% SALES TAX

CONT. USA INCLUDE \$3.00 SHIPPING, CANADA \$6.00, FOREIGN \$12.00 MASTERCARD, VISA, and C.O.D. ACCEPTED


To satisfy in-depth questions regarding our products send \$20.00 to receive full documentation, schematics, & source listings for all boards currently in production

THE GREAT DEBATE

SPEAK 'N' SING 2

VS.


SPEAK 'N' SING 1



NO YOU CAN'T

I CAN PLAY MUSIC


SO CAN I



ME TOO!

I HAVE MY OWN FIFO MEMORY JUST LIKE ME

MY SPEECH I HAVE AN IS IMPECCABLE VOCABULARY



WHATEVER YOUR CHOICE, YOU WIN THE MOST VERSATILE SYNTHESIZERS ON ANY BUS

Both the SPEAK 'N' SING 1 and the SPEAK 'N' SING 2 are ideally suited for a wide range of industrial, commercial, and entertainment applications such as: security systems, automatic telephone answering and originate devices, as an aid to the handicapped, teaching machines, and much more. Where an unlimited vocabulary is needed, the SPEAK 'N' SING 1 is ideal. When speech of exceptional quality is desired, the SPEAK 'N' SING 2 is perfect.

- Both synthesizers contain an on board FIFO memory buffer to reduce processor overhead and ease software development. None of the other popular bus oriented synthesizers has this feature.
- Each device has an on board audio power amplifier that easily drives an external speaker.
- Both synthesizers may be interrupt driven, however, the on board FIFO should reduce this need in most real time applications.
- A 60 page manual fully discusses speech, music, and sound effect synthesis.
- An 8 bit D/A converter is included on each board for the reproduction of MUSIC and SOUND EF-FECTS.
- A single voice music interpreter is also included which allows one to develop MUSIC easily. For example, to synthesize a half note C sharp in the first octave, merely enter C#1H.
- Software is available on 5" or 8" disks in FLEX 2.0 or FLEX 9.0 formats. Included are many utility programs as well as MUSIC, SOUND EFFECTS, and SPEECH games.

SPEAK 'N' SING 1 SPEECH SYNTHESIS

The SPEAK 'N' SING 1 uses a special large scale integrated circuit, the SC-01 by VOTRAX, to reproduce any one of 64 phonemes at 4 inflections. These phonemes allow one to rproduce any under in English as well as many other languages. Typically only 5 or 6 phonemes are needed for each word. Supplied software includes a powerful speech editor with a preprogramed 800+ word wordshulary.

SPEAK 'N' SING 2 SPEECH SYNTHESIS

The SPEAK 'N' SING 2 speech is based on the National Semiconductor DIGITALKER synthesis technique. The high quality of the speech is incredible and must be heard to really be appreciated. Each word is reproduced by storing a single one byte code. The standard word set is listed below and space is provided on the board for additional vocabulary which may be purchased separately.

ONE	FOURTEEN	NINETY	80HZ TONE	DOWN	HIGHER	MARK	PARENTHESIS	SET	Α	N
TWO	FIFTEEN	HUNDRED	20MS WAIT	EQUAL	HOUR	METER	PERCENT	SPACE	8	0
THREE	SIXTEEN	THOUSAND	40MS WAIT	ERROR	IN	MILE	PLEASE	SPEED	C	P
FOUR	SEVENTEEN	MILLION	80MS WAIT	FEET	INCHES	MILLI	PLUS	STAR	D	Q
FIVE	EIGHTEEN	ZERO	160MS WAIT	FLOW	IS	MINUS	POINT	START	E	R
SIX	NINETEEN	AGAIN	320MS WAIT	FUEL	IT	MINUTE	POUND	STOP	F	S
SEVEN	TWENTY	AMPERE	CENTI	GALLON	KILO	NEAR	PULSES	THAN	G	T
EIGHT	THIRTY	AND	CHECK	GO	LEFT	NUMBER	RATE	THE	H	U
NINE	FORTY	AT	COMMA	GRAM	LESS	OF	RE	TIME	1	٧
TEN	FIFTY	CANCEL	CONTROL	GREAT	LESSER	OFF	READY	TRY	J	W
ELEVEN	SIXTY	CASE	DANGER	GREATER	LIMIT	ON	RIGHT	UP	K	X
TWELVE	SEVENTY	CENT	DEGREE	HAVE	LOW	OUT	SS	VOLT	L	Y
THIRTEEN	EIGHTY	400Hz	DOLLAR	HIGH	LOWER	OVER	SECOND	WEIGHT	M	Z

THE GOOD NEWS

Write for information on additional word sets.

SS-2 SPEAK 'N' SING 2 assembled, tested, manual, disk. \$239.95

WD-1 Two additional ROMs with 131 words. \$49.95

SS-1 SPEAK 'N' SING 1 assembled, tested, manual, disk.
SA-1 As above without SC-01 speech synthesizer chip.

(Allows Alford & Assoc. VS-1 owners to upgrade.)

SF-21 Additional software (Games, Sound Effects, Music)

\$29.95

SF-1 Additional Software (Games, Sound Effects, Music)

SF-22 More software (Games, Sound Effects, Music)

(\$44.95 when ordered with SS-2)

\$29.95

SF-2 More Software (Games, Sound Effects, Music)

\$29.95

\$169.95

\$29.95

■FOR THE MUSIC LOVER

This 4 voice Stero Music Compiler easily allows the SPEAK 'N' SING 1, the SPEAK 'N' SING 2, or the NEWTECH Model 68 music synthesizer to reproduce 4 voice music. Written entirely in machine code, it compiles over 50 times faster than BASIC models. The compiler plays four voices simultaneously and allows tempo changes anywhere in the song. It also supports the reproduction of music in stereo. Other features include a 7 octave range, 45 different note durations, built in debugging capability, interface to FLEX files. IF statement for repeating sections and much more. Truely an incredibly powerful MUSIC compiler.

ME-1 \$39.95

1. BE SURE TO SPECIFY DISK SIZE AND FLEX FORMAT

2. We accept MASTERCARD, VISA, COD, and CHECKS

3 Illinois residents add 5% sales tax.

Postage prepaid on US orders.

5. Overseas orders add \$12 postage.

6. FLEX is a trademark of Technical Systems Consultants.

"WE'RE TALKING TO YOU"

Speech Systems

(312) 879-6880

38 W 255 DEERPATH ROAD BATAVIA, IL 60510

CALL ANY DAY, ANYTIME FOR DEMO AND/OR TO ORDER. YOU MAY ALSO ORDER BY MAIL.

SOFTWARE FOR PERCOM LFD-400

DIXIE a complete DOS package \$60

FEATURES: Dynamic allocation of disk space. 15 directory levels. 45 files per disk. 12 character names. Quick & easy conversion from MPX. RESIDENT COMMANDS: Create, release, rename, protect/unprotect, save, load, and execute FILE (at specified directory level). Create, release, and rename DIRECTORY LEVEL. Print disk label & number of free sectors. Print directory report (at specified level). Jump to address. UTILITIES: Convert MPX disk to DIXIE disk. Init disk. Change disk label. Single/dual drive disk copy. File copy. Directory report to printer. PATCHES: Percom SUPER BASIC, TOUCHUP editor, symbolic assembler, and HEXLDR. TSC cassette editor and assembler. SWTP 8K basic. REQUIRES: MIKBUG type monitor. MINIDOS 1.4. 800 words RAM. YOU GET: 2708 EPROM. 3 disks with source for all software. Manual.

XREF a cross reference patch \$15

Adds a symbol cross reference assembly option to the Percom assembler (base & DIXIE-modified versions). Source code supplied on disk. Manual.

Note that the Percom SUPER BASIC patch and the MPX-to-DIXIE disk conversion utility are both now completed and supplied with the DIXIE package.

Michigan residents add 4% Specify 35 or 40 trk drives

Check or money order Add \$2/order shipping

BLUE HAT SOFTWARE

BOX 4127 FLINT, MI 48504 313-738-2863 evenings

LFD-400, MPX, TOUCHUP, and MINIDOS are trademarks of Percom Data Co, Inc. MIKBUG is a trademark of Motorola, Inc.

HUMBUG

small and GREAT . . . at the same time!

In terms of size, our little HUMBUG is probably one of the smallest things you can add to your system. But in terms of utility, power, and convenience it may well be THE GREATEST!

HUMBUG is a monitor ROM which plugs into your CPU board instead of your present monitor and is a totally compatible replace-

ment. All the standard monitor commands and routines are there, and it will run the same software. But there is more.

HUMBUG is not just a monitor—it is also a complete debugging system. It has additional commands for displaying memory contents in various formats (including ASCII); filling, moving, searching, and checking memory contents; doing memory tests; inserting multiple breakpoints, even single-stepping through programs one instruction at a time. HUMBUG lets you start and stop programs from the keyboard—without pushing RESET. And when a program goes into 'never-never-land', HUMBUG can stop it and tell you where it was when stopped. But there is more.

HUMBUG provides full I/O control from the keyboard. Turn a printer port on and off; enable a user-written port; pause when the screen is full; even turn off your main terminal output and let the program run without being slowed down by output. A printer spooling feature provides a 1K RAM buffer for your printer, and overlaps printing with processing for greater speed. But there is more.

HUMBUG can support your video board. That and a keyboard can replace an expensive terminal, and provide greater speed and versatility as well. Allows simple cursor control, cursor read, and screen read too. But there is

HUMBUG is available for 6800, 6802, and 6809 CPU boards made by SWTP, Gimix, Percom, and Star-Kits. It supports a serial terminal, or video boards made by Percom, Thomas, or F&D. It comes in either 2708 or 2716 EPROMs, and in either 2K, 3K or 4K versions, at prices ranging from \$40 to \$75 which include a full manual and full source code. There are several versions, depending on your hardware configuration, and it's a good idea to get our catalog and HUMBUG spec sheet first. If you want it real fast, call us up any evening with a 300-baud modem and LIST HUMBUG.DAT on our computerized bulletin board. While you're at it, feel free to leave a message for other 68xx users on the system or even place an order.

STAR-KITS
P.O. Box 209, Mt. Kisco NY 10549 (914) 241-0287

6809 Relocating Recursive Macro Assembler & Loader/Linker with text editor

- •Runs on 6809 system (in as little as 32k)
- Interactive or non-interactive (batch) mode
- Supports relocatable and absolute code
- •Can assembler 6800 & 6801 source and generate 6809 object
- •CROSS ASSEMBLER MODE—can assemble 6800 & 6801 source and generate 6800 & 6801 object
- •8 character global and local labels
- •76 English error messages
- Alphabetized or non-alphabetized symbol table
- •Cross reference table
- •Checks for unreferenced labels
- •Can enable the insertion of a 'SWI' after every instruction
- •Supports the following assembler directives: ASECT, CSECT, PSECT, DEBUGS, END EQU, EXEC, EXT, FCB, FCC, ID, INT INCLUDE, NAM, OPT, ORG, PAG, RMB SET, SETDP, SPC, TTL, FDB
- Program sectioning (ASECT, CSECT, or PSECT)
- •Source of I/O routines supplied
- •Total FLEX* compatability
- •Powerful co-resident text editor
- TSC source file compatibility

Powerful Macro Capabilities

- 8 character symbolic (substitution) labels
- branch on conditions EQ, NE, LE, LT GT, GE
- supports nesting
- Logical, aritmetic, and string labels
- Sublist processing
- Powerful string functions such as SUBSTRING
- Supports the following directives
 ACNT, AGO, AIF, ANOP, GBLA, GBLB, GBLC
 LCLA, LCLB, LCLC, MACRO, MEND, MNOTE
 SETA, SETB, SETC

Loader/Linker

- Link and load (with offset)
- Link and save
- Global cross references
- Supports the following commands LOAD, COMPARE, SAVE, EDIT, LINK, MAP INTERNALS, UNDEFINED, CLEAR, RUN SECTION, FIX

MASM	6809	\$ 250.00

User's Manual Only (about 200 pages-refundable)\$ 25.00

A version of the above assembler which generates ABSOLUTE code is also available

ASMB 6809 ----- \$ 150.00

The above software is available on 5 or 8 inch FLEX* disks, prices include one year maintenance (single CPU). Even if you already own an assembler you should seriously consider ordering these powerful tools.

CINCITEK Software


Box 19365 Cincinnati, Ohio 45219

(513) 751-6203 (evenings)

Ohio residents add 4.5 % sales tax Add 2 % for postage Foreign orders add 10 %

Dealer Inquires Welcome

*FLEX is a trademark of TECHNICAL SYSTEM CONSULTANTS



- Convert your 6800 programs to 6809!
- Automatic LABEL generation
- Allows specifying FCB's, FCC's, FDB's, etc.
- Constants input from DISK or CONSOLE
- Automatically uses system variable NAMES
- DISK-to-DISK or DISK-to-CONSOLE operation Includes 5" or 8" FLEX 9 diskette with relocatable object code. Full operating instructions (you'll learn in minutes!)

Order your DYNAMITE[®] today
Only \$60.00 postpaid in U.S. MC & VISA accepted
6809, FLEX 9, and 24K total RAM required
order from:

COMPUTER SYSTEMS CENTER

13461 Olive Blvd. Chesterfield, MO 63017 (314) 576-5020



we also stock SWTPC, TSC, JPC products hours 10 a.m. to 6 p.m. Mon - Fri

Dealer inquiries welcome FLEX is a trademark of TSC (Bless their hearts)



JUDGE THE REST, THEN BUY THE BEST

Only GIMIX offers you **SOFTWARE SWITCHING** between **MICROWARE's OS-9** and **TSC's FLEX**. Plus you get the power of the GMXBUG system monitor with its advanced debugging utility, and memory manipulation routines. A wide variety of languages and other software is available for these two predominant 6809 Disk Operating Systems.

You can order a system to meet your needs, or select from the 6809 Systems featured below.

JUDGE THE FEATURES AND QUALITY OF GIMIX 6809 SYSTEMS

GIMIX' CLASSY CHASSIS™ is a heavyweight aluminum mainframe cabinet with back panel cutouts to conveniently connect your terminals, printers, drives, monitors, etc. A 3 position keyswitch lets you lock out the reset switch. The power supply features a ferro-resonant constant voltage transformer that supplies 8V at 30 amps, + 15V at 5 amps, and − 15V at 5 amps to insure against problems caused by adverse power input conditions. It supplies power for all the boards in a fully loaded system plus two 5 ¼'' drives (yes! even a Winchester) that can be installed in the cabinet. The Mother board has fifteen 50 pin and eight 30 pin slots to give you the most room for expansion of any SS50 system available. 11 standard baud rates from 75 to 38.4K are provided and the I/O section has its own extended addressing to permit the maximum memory address space to be used. The 2 Mhz 6809 CPU card has both a time of day clock with battery back-up and a 6840 programmable timer. It also contains 1K RAM, 4 PROM/ROM/RAM sockets, and provides for an optional 9511A or 9512 Arithmetic Processor. The RAM boards use high speed, low power STATIC memory that is fully compatible with any DMA technique. STATIC RAM requires no refresh timing, no wait states or clock stretching, and allows fast, reliable operation. The system includes a 2 port RS232 serial interface and cables. All GIMIX boards use gold plated bus connectors and are fully socketed. GIMIX designs, manufactures, and tests in-house its complete line of products. All boards are twice tested, and burned in electrically to insure reliability and freedom from infant mortality of component parts. All systems are assembled and then retested as a system after being configured to your specific order.

56KB 2MHZ 6809 SYSTEMS WITH GMXBUX/FLEX/OS-9 SOFTWARE SELECTABLE

With #58 single density disk controller	988.59
With #68 DMA double density disk controller\$32	248.49
to substitute Non-volatile CMOS RAM with battery back-up, add	. 300.00
for 50 Hz export power supply models, add	30.00

Either controller can be used with any combination of 5" and/or 8" drives, up to 4 drives total, have data recovery circuits (data separators), and are designed to fully meet the timing requirements of the controller I.C.s.

5 1/4" DRIVES INSTALLED IN THE ABOVE with all necessary cables

	SINGLE	DENSITY	DOUBLE		
	Formatted	Unformatted	Formatted	Unformatted	
40 track (48TPI) single sided	199,680	250,000	341,424	500,000	2 for \$700.00
40 track (48TPI) double sided	399,360	500,000	718,848	1,000,000	2 for 900.00
80 track (96TPI) single	404,480	500,000	728,064	1,000,000	2 for 900.00
80 track (96TPI) double	808,960	1,000,000	1,456,128	2,000,000	2 for 1300.00

Chart shows total capacity in Bytes for 2 drives.

Contact GIMIX for price and availability of 8" floppy disk drives and cabinets; and 5" and 8" Winchester hard disk system.

128KB 2Mhz 6809 DMA Systems for use with TSC's UNIFLEX or MICROWARES's OS-9 Level 2

(Software and drives not included)	
to substitute 128KB CMOS RAM with battery back-up, add	600.00
for each additional 64KB NMOS STATIC RAM board, add	639.67
for each additional 64KB CMOS STATIC RAM board, add	
for 50 Hz export power supply, add	

NOTE: UNIFLEX can not be used with 5" minifloppy drives.

GIMIX has a wide variety of RAM, ROM, Serial and Parallel I/O, Video, Graphics, and other SS50 bus cards that can be added now or in the future. Phone or write for more complete information and brochure.

THE SUN NEVER SETS ON GIMIX USERS

GIMIX Systems are found on every continent, except Antarctica. (Any users there? If so, please contact GIMIX so we can change this.) A representative group of GIMIX users includes: **Government Research and Scientific Organizations** in Australia, Canada, U.K., and in the U.S.; NASA, Oak Ridge, White Plains, Fermilab, Argonne, Scripps, Sloan Kettering, Los Alamos National Labs, AURA. **Universities:** Carleton, Waterloo, Royal Military College, in Canada; Trier in Germany; and in the U.S.; Stanford, SUNY, Harvard, UCSD, Mississippi, Georgia Tech. **Industrial users** in Hong Kong, Malaysia, South Africa, Germany, Sweden, and in the U.S.; GTE, Becton Dickinson, American Hoechst, Monsanto, Allied, Honeywell, Perkin Elmer, Johnson Controls, Associated Press, Aydin, Newkirk Electric, Revere Sugar, HI-G/AMS Controls, Chevron. **Computer mainframe and peripheral manufacturers**, IBM, OKI, Computer Peripherals Inc., Qume, Floating Point Systems. **Software houses**; Microware, T.S.C., Lucidata, Norpak, Talbot, Stylo Systems, AAA, HHH, Frank Hogg Labs, Epstein Associates, Softwest, Dynasoft, Research Resources U.K., Microworks, Analog Systems, Computerized Business Systems.



TO ORDER BY MAIL

SEND CHECK OR MONEY ORDER OR USE YOUR VISA OR MASTER CHARGE. Please allow 3 weeks for personal checks to clear. U.S. orders add \$5 handling if order is under \$200.00. Foreign orders add \$10 handling if order is under \$200.00.

Foreign orders over \$200.00 will be shipped via Emery Air Freight COLLECT, and we will charge no handling. All orders must be prepaid in U.S. funds. Please note that foreign checks have been taking about 8 weeks for collection so we would advise wiring money, or checks drawn on a bank account in the U.S.. Our bank is the Continental Illinois National Bank of Chicago, account #73-32033 Visa or Master Charge also accepted.

GIMIX INC. reserves the right to change pricing and product specifications at any time without further notice.

GIMIX® and GHOST® are registered trademarks of GIMIX Inc.

© 1981 GIMIX Inc.

FLEX AND Uniflex are trademarks of Technical Systems

Consultants Inc. OS-9 is a trademark of Microware Inc. See their ads for

other GIMIX compatible software

GIMIX Systems are chosen by the Pros because of quality, reliability and features.



The Company that delivers
Quality Electronic products since 1975.

1337 WEST 37th PLACE, CHICAGO, IL 60609 (312) 927-5510 • TWX 910-221-4055